

<b>Configuration API</b>	1
.....	3
BS2FactoryConfig	3
BS2SystemConfig	4
BS2AuthConfig	6
BS2StatusConfig	8
BS2DisplayConfig	9
BS2IpConfig	12
BS2IpConfigExt	14
BS2TNAConfig	14
BS2CardConfig	16
BS2FingerprintConfig	18
BS2Rs485Config	20
BS2WiegandConfig	22
BS2WiegandDeviceConfig	25
BS2InputConfig	26
BS2WlanConfig	27
BS2Trigger	28
BS2Action	30
BS2TriggerActionConfig	35
BS2EventConfig	35
BS2WiegandMultiConfig	36
BS1CardConfig	36
BS2SystemConfigExt	38
BS2VoipConfig	38
BS2FaceConfig	39
BS2Rs485ConfigEX	44
BS2CardConfigEx	45
BS2DstConfig	46
BS2Configs	47
BS2IPV6Config	49
BS2DesFireCardConfigEx	50
BS2AuthConfigExt	51
BS2FaceConfigExt	54
BS2ThermalCameraConfig	57
BS2BarcodeConfig	57
BS2InputConfigEx	59
BS2RelayActionConfig	60
BS2VoipConfigExt	62
BS2RtspConfig	64
BS2License	65
BS2LicenseConfig	66
BS2BarcodeConfig	66
BS2OsdpStandardConfig	68
BS2OsdpStandardActionConfig	70
BS2CustomMifareCard	73
BS2CustomDesFireCard	74
BS2CustomCardConfig	75

# Configuration API

## API

- **BS2\_ResetConfig:** ( )
- **BS2\_ResetConfigExceptNetInfo:** ( )
- **BS2\_GetConfig:** Configuration blob 가
- **BS2\_SetConfig:** Configuration blob
- **BS2\_GetFactoryConfig:** 가
- **BS2\_GetSystemConfig:** 가
- **BS2\_SetSystemConfig:** 가
- **BS2\_GetAuthConfig:** 가
- **BS2\_SetAuthConfig:** 가
- **BS2\_GetStatusConfig:** led, buzzer 가
- **BS2\_SetStatusConfig:** led, buzzer
- **BS2\_GetDisplayConfig:** UI 가
- **BS2\_SetDisplayConfig:** UI
- **BS2\_GetIPConfig:** IP 가
- **BS2\_SetIPConfigViaUDP:** IP UDP broadcasting 가
- **BS2\_SetIPConfig:** IP
- **BS2\_SetIPConfigViaUDP:** IP UDP broadcasting
- **BS2\_GetIPConfigExt:** DNS Server URL 가
- **BS2\_SetIPConfigExt:** DNS Server URL
- **BS2\_GetTNAConfig:** TNA 가
- **BS2\_SetTNAConfig:** TNA
- **BS2\_GetCardConfig:** 가
- **BS2\_SetCardConfig:** 가
- **BS2\_GetFingerprintConfig:** 가
- **BS2\_SetFingerprintConfig:** 가
- **BS2\_GetRS485Config:** RS485 가
- **BS2\_SetRS485Config:** RS485
- **BS2\_GetWiegandConfig:** Wiegand 가
- **BS2\_SetWiegandConfig:** Wiegand
- **BS2\_GetWiegandDeviceConfig:** Wiegand 가
- **BS2\_SetWiegandDeviceConfig:** Wiegand
- **BS2\_GetInputConfig:** Supervised 가
- **BS2\_SetInputConfig:** Supervised
- **BS2\_GetWlanConfig:** 가
- **BS2\_SetWlanConfig:** 가
- **BS2\_GetTriggerActionConfig:** Trigger action 가
- **BS2\_SetTriggerActionConfig:** Trigger action
- **BS2\_GetEventConfig:** Image log filter 가
- **BS2\_SetEventConfig:** Image log filter
- **BS2\_GetWiegandMultiConfig:** WiegandMulti 가
- **BS2\_SetWiegandMultiConfig:** WiegandMulti
- **BS2\_GetCard1xConfig:** V1.x Template On Card  
가
- **BS2\_SetCard1xConfig:** V1.x Template On Card
- **BS2\_GetSystemExtConfig:** Master Slave 가

- **BS2\_SetSystemExtConfig:** Master Slave 가
- **BS2\_GetVoipConfig:** Voip 가
- **BS2\_SetVoipConfig:** Voip
- **BS2\_GetFaceConfig:** Face 가
- **BS2\_SetFaceConfig:** Face
- **BS2\_GetRS485ConfigEx:** CoreStation RS485 가
- **BS2\_SetRS485ConfigEx:** CoreStation RS485
- **BS2\_GetCardConfigEx:** iClass SEOS 가
- **BS2\_SetCardConfigEx:** iClass SEOS
- **BS2\_GetDstConfig:** DST 가
- **BS2\_SetDstConfig:** DST
- **BS2\_GetSupportedConfigMask:** 가
- **BS2\_GetIPConfigViaUDPEx:** [+ 2.6.3] IP UDP broadcasting 가 (host ip )
- **BS2\_SetIPConfigViaUDPEx:** [+ 2.6.3] IP UDP broadcasting (host ip )
- **BS2\_GetIPV6Config:** [+ 2.6.3] IP V6 가
- **BS2\_SetIPV6Config:** [+ 2.6.3] IP V6
- **BS2\_GetIPV6ConfigViaUDP:** [+ 2.6.3] IP V6 UDP broadcasting 가
- **BS2\_SetIPV6ConfigViaUDP:** [+ 2.6.3] IP V6
- **BS2\_GetIPV6ConfigViaUDPEx:** [+ 2.6.3] IP V6 UDP broadcasting 가 (host ip )
- **BS2\_SetIPV6ConfigViaUDPEx:** [+ 2.6.3] IP V6 UDP broadcasting (host ip )
- **BS2\_GetDesFireCardConfigEx:** [+ 2.6.4] DesFire 가
- **BS2\_SetDesFireCardConfigEx:** [+ 2.6.4] DesFire
- **BS2\_GetAuthConfigExt:** [+ 2.7.1] FSF2 가
- **BS2\_SetAuthConfigExt:** [+ 2.7.1] FSF2
- **BS2\_GetFaceConfigExt:** [+ 2.7.1] FSF2, FS2 가
- **BS2\_SetFaceConfigExt:** [+ 2.7.1] FSF2, FS2
- **BS2\_GetThermalCameraConfig:** [+ 2.7.1] FSF2, FS2 가
- **BS2\_SetThermalCameraConfig:** [+ 2.7.1] FSF2, FS2
- **BS2\_GetBarcodeConfig:** [+ 2.8] XS2 Barcode 가
- **BS2\_SetBarcodeConfig:** [+ 2.8] XS2 Barcode
- **BS2\_GetInputConfigEx:** [+ 2.8.1] IM-120 Input 가
- **BS2\_SetInputConfigEx:** [+ 2.8.1] IM-120 Input
- **BS2\_GetRelayActionConfig:** [+ 2.8.1] IM-120 RelayAction 가
- **BS2\_SetRelayActionConfig:** [+ 2.8.1] IM-120 RelayAction
- **BS2\_GetVoipConfigExt:** [+ 2.8.3] BS3 VoIP 가
- **BS2\_SetVoipConfigExt:** [+ 2.8.3] BS3 VoIP
- **BS2\_GetRtspConfig:** [+ 2.8.3] BS3 RTSP 가
- **BS2\_SetRtspConfig:** [+ 2.8.3] BS3 RTSP
- **BS2\_GetLicenseConfig:** [+ 2.9.1] 가
- **BS2\_GetOsdpStandardConfig:** [+ 2.9.1] OSDP 가
- **BS2\_GetOsdpStandardActionConfig:** [+ 2.9.1] OSDP action LED/buzzer 가
- **BS2\_SetOsdpStandardActionConfig:** [+ 2.9.1] OSDP action LED/buzzer
- **BS2\_GetCustomCardConfig:** [+ 2.9.4] Custom smart card 가
- **BS2\_SetCustomCardConfig:** [+ 2.9.4] Custom smart card

## BS2FactoryConfig

```
typedef struct {
    uint8_t major;
    uint8_t minor;
    uint8_t ext;
    uint8_t reserved[1];
} Version;

typedef struct {
    uint32_t deviceID;
    uint8_t macAddr[BS2_MAC_ADDR_LEN];
    uint8_t reserved[2];
    char modelName[BS2_MODEL_NAME_LEN];
    Version boardVer;
    Version kernelVer;
    Version bscoreVer;
    Version firmwareVer;
    char kernelRev[BS2_KERNEL_REV_LEN];
    char bscoreRev[BS2_BSCORE_REV_LEN];
    char firmwareRev[BS2_FIRMWARE_REV_LEN];
    uint8_t reserved2[32];
} BS2FactoryConfig;
```

1. *deviceID*

2. *macAddr*

3. *reserved*

4. *modelName*

5. *boardVer*

6. *kernelVer*

7. *bscoreVer*

BioStar core

8. *firmwareVer*

9. *kernelRev*

10. *bscoreRev*  
BioStar core

11. *firmwareRev*

12. *reserved2*

## BS2SystemConfig

```
typedef struct {
    uint8_t notUsed[16 * 16 * 3];
    int32_t timezone;
    uint8_t syncTime;
    uint8_t serverSync;
    uint8_t deviceLocked;
    uint8_t useInterphone;
    uint8_t useUSBConnection;
    uint8_t keyEncrypted;
    uint8_t useJobCode;
    uint8_t useAlphanumericID;
    uint32_t cameraFrequency;
    bool secureTamper;
    bool reserved0;      // (write protected)
    uint8_t reserved[2];
    uint32_t useCardOperationMask;
    uint8_t reserved2[16];
} BS2SystemConfig;
```

1. *notUsed*

2. *timezone*  
(sec)

3. *syncTime*  
BioStar  
flag

4. *serverSync*

5. *deviceLocked*  
. ( . )

6. *useInterphone*  
flag

7. *useUSBConnection*  
member . (USB 가 .)

8. *keyEncrypted*

OSDP secure key

flag

9. *useJobCode*

Job code

flag

10. *useAlphanumericID*

AlphanumericID

flag

11. *cameraFrequency*

camera

1	50Hz
2	60Hz

12. *secureTamper*

flag

on

가

.

(

,

, SSL

)

13. *reserved0*14. *reserved*15. *useCardOperationMask*

[ + 2.6.4]

MASK

가

가

, 가

CARD\_OPERATION\_USE

EM

useCardOperationMask

0x80000001

0xFFFFFFFF	CARD_OPERATION_MASK_DEFAULT
0x80000000	CARD_OPERATION_USE
0x00000000	CARD_OPERATION_MASK_NONE
0x00000800	CARD_OPERATION_MASK_CUSTOM_DESFIRE_EV1
0x00000400	CARD_OPERATION_MASK_CUSTOM_CLASSIC_PLUS
0x00000200	CARD_OPERATION_MASK_BLE
0x00000100	CARD_OPERATION_MASK_NFC
0x00000080	CARD_OPERATION_MASK_SEOS
0x00000040	CARD_OPERATION_MASK_SR_SE
0x00000020	CARD_OPERATION_MASK_DESFIRE_EV1
0x00000010	CARD_OPERATION_MASK_CLASSIC_PLUS
0x00000008	CARD_OPERATION_MASK_ICLASS
0x00000004	CARD_OPERATION_MASK_MIFARE_FELICA
0x00000002	CARD_OPERATION_MASK_HIDPROX

0x00000001	CARD_OPERATION_MASK_EM

16. reserved2

## BS2AuthConfig

```
typedef struct {
    uint32_t authSchedule[BS2_NUM_OF_AUTH_MODE];
    uint8_t useGlobalAPB;
    uint8_t globalAPBFailAction;
    uint8_t useGroupMatching;
    uint8_t reserved;
    uint8_t reserved[28];
    uint8_t usePrivateAuth;
    uint8_t faceDetectionLevel;
    uint8_t useServerMatching;
    uint8_t useFullAccess;
    uint8_t matchTimeout;
    uint8_t authTimeout;
    uint8_t numOperators;
    uint8_t reserved2[1];
    struct {
        char userID[BS2_USER_ID_SIZE];
        uint8_t level;
        uint8_t reserved[3];
    } operators[BS2_MAX_OPERATORS];
} BS2AuthConfig;
```

1. authSchedule

가  
가 ,  
0

0	BS2_AUTH_MODE BIOMETRIC ONLY	
1	BS2_AUTH_MODE BIOMETRIC PIN	+ PIN
2	BS2_AUTH_MODE CARD ONLY	
3	BS2_AUTH_MODE CARD BIOMETRIC	+
4	BS2_AUTH_MODE CARD PIN	+ PIN

5	BS2_AUTH_MODE_CARD_BIOMETRIC_OR_PIN	+ or PIN
6	BS2_AUTH_MODE_CARD_BIOMETRIC_PIN	+ + PIN
7	BS2_AUTH_MODE_ID_BIOMETRIC	ID +
8	BS2_AUTH_MODE_ID_PIN	ID + PIN
9	BS2_AUTH_MODE_ID_BIOMETRIC_OR_PIN	ID + or PIN
10	BS2_AUTH_MODE_ID_BIOMETRIC_PIN	ID + + PIN

2. *useGlobalAPB*

flag

3. *globalAPBFailAction*

BioStar

0	APB
1	Soft APB
2	Hard APB

4. *useGroupMatching*

flag

5. *reserved*6. *usePrivateAuth*

flag

7. *faceDetectionLevel*

A2

Normal/Strict

가  
0

가

0	
1	Normal mode
2	Strict mode

A2	가	, FaceStation2	FaceLite
----	---	----------------	----------

8. *useServerMatching*

Matching server

flag

9. *useFullAccess*10. *matchTimeout*

(sec)

11. *authTimeout*

(sec)

12. *numOperators*

operator

13. *reserved2*14. *userID*15. *level*

가

0	
1	
2	
3	

Operator	가	, 가	operator	<b>numOperators</b>
----------	---	-----	----------	---------------------

16. *reserved***BS2StatusConfig**

```
typedef struct {
    struct {
        uint8_t enabled;
        uint8_t reserved[1];
        uint16_t count;
    }
}
```

```

        BS2LedSignal signal[BS2_LED_SIGNAL_NUM];
    } led[BS2_DEVICE_STATUS_NUM];
    uint8_t reserved1[32];
    struct {
        uint8_t enabled;
        uint8_t reserved[1];
        uint16_t count;
        BS2BuzzerSignal signal[BS2_BUZZER_SIGNAL_NUM];
    } buzzer[BS2_DEVICE_STATUS_NUM];
    uint8_t configSyncRequired;
    uint8_t reserved2[31];
} BS2StatusConfig;

```

1. *enabled*

led flag .

2. *reserved*

3. *count*

led signal , 0 .

4. *signal*

led signal pattern , 3 .

5. *reserved1*

6. *enabled*

buzzer flag .

7. *reserved*

8. *count*

buzzer signal , 0 .

9. *signal*

buzzer signal pattern , 3 . 10. *configSyncRequired*  
configuration , true .

11. *reserved2*

## BS2DisplayConfig

```

typedef struct {
    uint32_t language;
    uint8_t background;
    uint8_t volume;
    uint8_t bgTheme;
}

```

```
    uint8_t dateFormat;
    uint16_t menuTimeout;
    uint16_t msgTimeout;
    uint16_t backlightTimeout;
    uint8_t displayDateTime;
    uint8_t useVoice;
    uint8_t timeFormat;
    uint8_t homeFormation;
    BS2_BOOL useUserPhrase;
    BS2_BOOL queryUserPhrase;
    uint8_t shortcutHome[BS2_MAX_SHORTCUT_HOME];
    uint8_t tnaIcon[16];
    uint8_t useScreenSaver;
    uint8_t show0sdpResult;
    uint8_t reserved1[30];
}
BS2DisplayConfig;
```

## 1. language

0	
1	
2	

## *2. background*

0	LOGO
1	NOTICE
2	SLIDE
3	PDF

### 3. volume

0-100 . 0

#### 4. *bqTheme*

0	
1	
2	Slide show
3	PDF

## 5. *dateFormat*

0	YYYY/MM/DD

1	MM/DD/YYYY
2	DD/MM/YYYY

6. *menuTimeout*

sec	. 0	(sec)	. 0-255
-----	-----	-------	---------

0	
10	10
20	20 ( )
30	30
40	40
50	50
60	60

7. *msgTimeout*

(ms) . 500-5000 ms

500	500
1000	1
2000	2 ( )
3000	3
4000	4
5000	5

8. *backlightTimeout*

(sec)

0	0
10	10
20	20 ( )
30	30
40	40
50	50
60	60

9. *displayDateTime*

flag

10. *useVoice*

voice instruction

flag

11. *timeFormat*

0	12
1	24

, Linux              BioStation 2, BioStation L2,  
 BioLite Net2, FaceLite              가  
 . (0 = 24 hour / 1 = 12 hour)

## 12. *homeFormation*

Home

1	
2	Shortcut 1
3	Shortcut 2
4	Shortcut 3
5	Shortcut 4

## 13. *useUserPhrase*

## 14. *queryUserPhrase*

true ,

## 15. *shortcutHome*

homeFormation

## 16. *tnalcon*

## 17. *useScreenSaver*

FaceStation 2, FaceStation F2 true ,              가

## 18. *showOsdpResult*

[+ 2.9.6] Intelligent slave

0	OSDP              ( )
1	OSDP

## 19. *reserved1*

## BS2IpConfig

```
typedef struct {
    uint8_t connectionMode;
    uint8_t useDHCP;
    uint8_t useDNS;
```

```

    uint8_t reserved[1];
    char ipAddress[BS2_IPV4_ADDR_SIZE];
    char gateway[BS2_IPV4_ADDR_SIZE];
    char subnetMask[BS2_IPV4_ADDR_SIZE];
    char serverAddr[BS2_IPV4_ADDR_SIZE];
    uint16_t port;
    uint16_t serverPort;
    uint16_t mtuSize;
    uint8_t baseband;
    uint8_t reserved2[1];
    uint16_t sslServerPort
    uint8_t reserved3[30];
} BS2IpConfig;

```

1. *connectionMode*

BioStar  
mode(0x1) direct mode BioStar  
가 BioStar

BioStar	, direct mode	BioStar	direct mode(0x0) server
			server mode
			direct mode

2. *useDHCP*

DHCP flag

3. *useDNS*

server addressss server URL flag

4. *reserved*5. *ipAddress*

IP

6. *gateway*

IP

7. *subnetMask*8. *serverAddr*

connectionMode가 server mode , BioStar IP

9. *port*

IP

10. *serverPort*

connectionMode가 server mode , BioStar

11. *mtuSize*

TCP MTU<sup>1)</sup>

12. *baseband*

baseband 10mb/s 100mb/s 가

13. *reserved2*

14. *sslServerPort*  
 connectionMode가 server ssl mode , BioStar

15. *reserved3*

## BS2IpConfigExt

```
typedef struct {
    char dnsAddr[BS2_IPV4_ADDR_SIZE];
    char serverUrl[BS2_URL_SIZE];
    uint8_t reserved[32];
} BS2IpConfigExt;
```

1. *dnsAddr*  
 dns
2. *serverUrl*  
 BioStar URL , 256
3. *reserved*

## BS2TNAConfig

```
typedef struct {
    uint8_t tnaMode;
    uint8_t tnaKey;
    uint8_t tnaRequired;
    uint8_t reserved[1];
    uint32_t tnaSchedule[BS2_MAX_TNA_KEY];
    uint8_t unused[BS2_MAX_TNA_KEY];
} BS2TNAInfo;

typedef struct {
    char tnaLabel[BS2_MAX_TNA_KEY][BS2_MAX_TNA_LABEL_LEN];
    uint8_t unused[BS2_MAX_TNA_KEY];
} BS2TNAExtInfo;

typedef struct {
    BS2TNAInfo tnaInfo;
    BS2TNAExtInfo tnaExtInfo;
    uint8_t reserved2[32];
} BS2TNAConfig;
```

1. *tnaMode*

0	
1	
2	
3	가
4	

2. *tnaKey*

Device Type	T&A Code	Mapped Key	Value
BioStation 2	BS2_TNA_UNSPECIFIED	(N/A)	0
	BS2_TNA_KEY_1	F1	1
	BS2_TNA_KEY_2	F2	2
	BS2_TNA_KEY_3	F3	3
	BS2_TNA_KEY_4	F4	4
	BS2_TNA_KEY_5	1	5
	BS2_TNA_KEY_6	2	6
	BS2_TNA_KEY_7	3	7
	BS2_TNA_KEY_8	4	8
	BS2_TNA_KEY_9	5	9
	BS2_TNA_KEY_10	6	10
	BS2_TNA_KEY_11	7	11
	BS2_TNA_KEY_12	8	12
	BS2_TNA_KEY_13	9	13
	BS2_TNA_KEY_14	Call	14
	BS2_TNA_KEY_15	0	15
	BS2_TNA_KEY_16	Esc	16

3. *tnaRequired*

가 1

flag

4. *reserved*5. *tnaSchedule*

가

6. *unused*7. *tnaLabel*8. *unused*

## BS2CardConfig

```
typedef struct {
    uint8_t primaryKey[6];
    uint8_t reserved1[2];
    uint8_t secondaryKey[6];
    uint8_t reserved2[2];
    uint16_t startBlockIndex;
    uint8_t reserved[6];
} BS2MifareCard;

typedef struct {
    uint8_t primaryKey[8];
    uint8_t secondaryKey[8];
    uint16_t startBlockIndex;
    uint8_t reserved[6];
} BS2IClassCard;

typedef struct {
    uint8_t primaryKey[16];
    uint8_t secondaryKey[16];
    uint8_t appID[3];
    uint8_t fileID;
    uint8_t encryptionType;
    uint8_t operationMode;
    uint8_t reserved[2];
} BS2DesFireCard;

typedef struct {
    uint8_t byteOrder;
    uint8_t useWiegandFormat;
    uint8_t dataType;
    uint8_t useSecondaryKey;
    BS2MifareCard mifare;
    BS2IClassCard iclass;
    BS2DesFireCard desfire;
    uint8_t formatID;
    uint8_t cipher;
    uint8_t smartCardByteOrder;
    uint8_t reserved[22];
} BS2CardConfig;
```

1. *primaryKey*  
Mifare card

2. *reserved1*

3. *secondaryKey*  
Mifare card

4. reserved2

5. startBlockIndex

Mifare data storage

start block index

6. reserved

7. primaryKey

IClass card

8. secondaryKey

IClass card

9. startBlockIndex

Mifare data storage

start block index

10. reserved

11. primaryKey

DesFire card

12. secondaryKey

DesFire card

13. appID

DESFire

14. fileID

DESFire

가

15. encryptionType

0	DES/3DES
1	AES

16. operationMode

(        )

0	(PICC master key      )
1	(App master key      )

17. reserved

18. byteOrder

. 0                  MSB<sup>2)</sup>                  , 1                  LSB<sup>3)</sup>

19. *useWiegandFormat*

Wiegand flag .

20. *dataType*

Card .

0	
1	
2	UTF16
3	BCD

21. *useSecondaryKey*

flag .

22. *formatID*

BioStar card configuration .

가

23. *cipher*

Keypad card id .

0 , Xpass 2, Xpass D2 Gangbox Keypad .

0	
1	

24. *smartCardByteOrder*[ + 2.8.2] smart card data MSB  
LSB controller , byte 가

smartCardByteOrder , MSB/LSB .

0	MSB
1	LSB

25. *reserved***BS2FingerprintConfig**

```
typedef struct {
    uint8_t      securityLevel;
    uint8_t      fastMode;
    uint8_t      sensitivity;
    uint8_t      sensorMode;
    uint16_t     templateFormat;
    uint16_t     scanTimeout;
    uint8_t      successiveScan;
```

```
    uint8_t      advancedEnrollment;
    uint8_t      showImage;
    uint8_t      lfdLevel;
    bool         checkDuplicate;

    uint8_t      reserved3[31];
} BS2FingerprintConfig;
```

## 1. securityLevel

0	
1	
2	

## 2. *fastMode*

0	
1	
2	
3	

### 3. *sensitivity*

0	가
1	1
2	2
3	3
4	4
5	5
6	6
7	가

#### 4. *sensorMode*

## 5. *templateFormat*

0	suprema
1	
2	Ansi

6. *scanTimeout*

10

7. *successiveScan*

8. *advancedEnrollment*

BS_SDK_ERROR_EXTRACTION_LOW_QUALITY	flag
BS_SDK_ERROR_CAPTURE_LOW_QUALITY	BS2_ScanFingerprint

9. *showImage*

flag

10. *fdLevel*

0	
1	
2	
3	

11. *checkDuplicate*

[+ V2.6.4] true

12. *reserved3*

## BS2Rs485Config

```

typedef struct {
    uint8_t supportConfig;
    uint8_t useExceptionCode;
    uint8_t exceptionCode[BS2_RS485_MAX_FAIL_CODE_LEN];
    uint8_t outputFormat;
    uint8_t osdpID;
    uint8_t reserved[4];
} BS2IntelligentPDInfo;

typedef struct {
    uint32_t baudRate;
    uint8_t channelIndex;
    uint8_t useResistance;
    uint8_t numDevices;
    uint8_t reserved[1];
    BS2Rs485SlaveDevice slaveDevices[BS2_RS485_MAX_SLAVES_PER_CHANNEL];
} BS2Rs485Channel;

typedef struct {

```

```

    uint8_t mode;
    uint8_t num0fChannels;
    uint8_t reserved[2];
    BS2IntelligentPDIInfo intelligentInfo;
    uint8_t reserved1[16];
    BS2Rs485Channel channels[BS2_RS485_MAX_CHANNELS];
} BS2Rs485Config;

```

1. *supportConfig*

[+V2.8] 0

Intelligent PD(Peripheral Device)

2. *useExceptionCode*

[+V2.8]

3. *exceptionCode*

[+V2.8]

가

가 0(0x0000000000000000)

가

4. *outputFormat*

[+V2.8]

0 ID가, 1

ID가

5. *osdpID*

[+V2.8] ACU

0~127 unique

6. *reserved*

[+V2.8]

7. *baudRate*

RS485

9600
19200
38400
57600
115200

8. *channelIndex*

( 가) RS485 network

9. *useResistance*

flag

10. *numOfDevices*

11. reserved

12. slaveDevices

32

13. mode

RS485

flag

0	
1	Master
2	Slave
3	Standalone

14. numOfChannels

RS485

15. reserved

16. intelligentInfo

[+V2.8] Intelligent Slave

, mode가 default(Standalone)

가

OSDP

17. reserved1

18. channels

RS485

4

## BS2WiegandConfig

```

typedef struct {
    uint32_t length;
    uint8_t idFields[BS2_WIEGAND_MAX_FIELDS][BS2_WIEGAND_FIELD_SIZE];
    uint8_t parityFields[BS2_WIEGAND_MAX_PARITIES][BS2_WIEGAND_FIELD_SIZE];
    BS2_WIEGAND_PARITY parityType[BS2_WIEGAND_MAX_PARITIES];
    uint8_t parityPos[BS2_WIEGAND_MAX_PARITIES];
} BS2WiegandFormat;

typedef struct {
    uint8_t mode;
    uint8_t useWiegandBypass;
    uint8_t useFailCode;
    uint8_t failCode;
    uint16_t outPulseWidth;
    uint16_t outPulseInterval;
}

```

```

    uint32_t formatID;
    BS2WiegandFormat format;
    uint16_t wiegandInputMask;
    uint16_t wiegandCardMask;
    uint8_t wiegandCSNIndex;
    uint8_t useWiegandUserID;
    uint8_t reserved[26];
} BS2WiegandConfig;

```

1. *length*  
Wiegand

2. *idFields*

4	id field	가	field	id	bit	
						, Standard 26bit wiegand card data "P FFFFFFFF"
						Facility Code "0 11111111
			0000000000000000 0 "	0x01FE0000	가	, Card Number 0x0001FFFE

```

// for Facility Code
idFields[][][28] = 0x01;
idFields[][][29] = 0xFE;
idFields[][][30] = 0x00;
idFields[][][31] = 0x00;

// for Card Number
idFields[1][28] = 0x00;
idFields[1][29] = 0x01;
idFields[1][30] = 0xFF;
idFields[1][31] = 0xFE;

```

3. *parityFields*

4	가	,	id Field	
---	---	---	----------	--

4. *parityType*

0	parity
1	parity
2	parity

5. *parityPos*  
Wiegand

6. *mode*  
Wiegand

0	
1	

2	

## 7. *useWiegandBypass*

0	
1	

## 8. *useFailCode*

## Fail Code

### 9. failCode

## Fail Code

0x00  
0xFF

#### 10. *outPulseWidth*

20 ~ 100 us 가

### 11. *outPulseInterval*

200 ~ 20000 μs 가

### 12. formatID

Wiegand

13. format

## WiegandFormat

#### 14. wiegandInputMask

Master              Slave    wiegand              wiegand              mask

### 15. wiegandCardMask

Master mask

## 16. wiegandCSNIndex

Mifare	EM	Wiegand out
BS2CardConfig		useWiegandFormat

#### 17. useWiegandUserID

Wiegand Card ID ID

0	
1	Card ID
2	ID

## 18. reserved

## BS2WiegandDeviceConfig

```
typedef struct {
    uint32_t deviceID;
    uint16_t port;
    uint8_t switchType;
    uint8_t reserved[1];
} BS2WiegandTamperInput;

typedef struct {
    uint32_t deviceID;
    uint16_t port;
    uint8_t reserved[10];
} BS2WiegandLedOutput;

typedef struct {
    uint32_t deviceID;
    uint16_t port;
    uint8_t reserved[34];
} BS2WiegandBuzzerOutput;

typedef struct {
    BS2WiegandTamperInput tamper;
    BS2WiegandLedOutput led[BS2_WIEGAND_STATUS_NUM];
    BS2WiegandBuzzerOutput buzzer;
    uint32_t reserved[32];
} BS2WiegandDeviceConfig;
```

## 1. *deviceID*

## Wiegand card reader tamper

## 2. port

Wiegand card reader tamper

### 3. *switchType*

가 'off'

가 on

trigger

0	Normally Open
1	Normally Closed

#### 4. reserved

## 5. deviceID

Wiegand card reader led

6. port

Wiegand card reader led

## 7. reserved

8. *deviceID*

Wiegand card reader    buzzer

9. *port*

Wiegand card reader    buzzer

10. *reserved*10. *led*

Wiegand card reader    led

2

0	led
1	led

**BS2InputConfig**

```

typedef struct {
    uint16_t minValue;
    uint16_t maxValue;
} BS2SVInputRange;

typedef struct {
    uint32_t deviceID;
    uint16_t port;
    uint8_t reserved[10];
} BS2WiegandLedOutput;

typedef struct {
    BS2SVInputRange shortInput;
    BS2SVInputRange openInput;
    BS2SVInputRange onInput;
    BS2SVInputRange offInput;
} BS2SupervisedInputConfig;

typedef struct {
    uint8_t numInputs;
    uint8_t numSupervised;
    uint16_t reseved;
    struct {
        uint8_t portIndex;
        uint8_t enabled;
        uint8_t supervised_index;
        uint8_t reserved[5];
        BS2SupervisedInputConfig config;
    } supervised_inputs[BS2_MAX_INPUT_NUM];
} BS2InputConfig;

```

1. *minValue*

0 ~ 3300(3.3v)

2. *maxValue*

0 ~ 3300(3.3v)

3. *shortInput*

short input

4. *openInput*

open input

5. *onInput*

on input

6. *offInput*

off input

7. *numInputs*8. *numSupervised*

supervised

9. *portIndex*10. *enabled*

supervised input

flag

11. *supervised\_index*

supervised input

0	1k
1	2.2k
2	4.7k
3	10k
255	

12. *reserved*13. *config*

supervised

가

, supervised input

**BS2WlanConfig**

```
typedef struct {
    uint8_t enabled;
```

```

    uint8_t operationMode;
    uint8_t authType;
    uint8_t encryptionType;
    char essid[BS2_WLAN_SSID_SIZE];
    char authKey[BS2_WLAN_KEY_SIZE];
    uint8_t reserved2[32];
} BS2WlanConfig;

```

1. *enabled*

2. *operationMode*

0	infrastructure
1	Ad-hoc

3. *authType*

0	Open
1	Shared
2	WPA-PSK
3	WPA2-PSK

4. *encryptionType*

0	
1	WEP
2	TKIP/AES
3	AES
3	TKIP

5. *essid*

6. *authKey*

7. *reserved*

## BS2Trigger

```

typedef struct {
    uint16_t code;

```

```
    uint8_t reserved[2];
} BS2EventTrigger;

typedef struct {
    uint8_t port;
    uint8_t switchType;
    uint16_t duration;
    uint32_t scheduleID;
} BS2InputTrigger;

typedef struct {
    uint32_t type;
    uint32_t scheduleID;
} BS2ScheduleTrigger;

typedef struct {
    uint32_t deviceID;
    uint8_t type;
    uint8_t reserved;
    uint16_t ignoreSignalTime;
}

union {
    BS2EventTrigger event;
    BS2InputTrigger input;
    BS2ScheduleTrigger schedule;
}
} BS2Trigger;
```

## 1. code

## 2. reserved

### 3. *port*

,

#### 4. *switchType*

가 'off'

가 on trigger

0	Normally Open
1	Normally Closed

## 5. duration

trigger

(ms) , 100

### 6. scheduleID

trigger

### 7. type

schedule trigger

0	schedule trigger
1	schedule trigger

8. *scheduleID*

trigger

9. *deviceID*

trigger

10. *type*

trigger

0	None
1	Event trigger
2	Input trigger
3	Schedule trigger

11. *reserved*

12. *ignoreSignalTime*

[+2.9.6]

가

가

wiegand

가

## BS2Action

```

typedef struct {
    uint32_t signalID;
    uint16_t count;
    uint16_t onDuration;
    uint16_t offDuration;
    uint16_t delay;
} BS2Signal;

typedef struct {
    uint8_t portIndex;
    uint8_t reserved[3];
    BS2Signal signal;
} BS2OutputPortAction;

typedef struct {
    uint8_t relayIndex;
    uint8_t reserved[3];
    BS2Signal signal;
}

```

```
} BS2RelayAction;

typedef struct {
    uint8_t color;
    uint8_t reserved[1];
    uint16_t duration;
    uint16_t delay;
} BS2LedSignal;

typedef struct {
    uint16_t count;
    uint8_t reserved[2];
    BS2LedSignal signal[3];
} BS2LedAction;

typedef struct {
    uint8_t tone;
    uint8_t fadeout;
    uint16_t duration;
    uint16_t delay;
} BS2BuzzerSignal;

typedef struct {
    uint16_t count;
    uint8_t reserved[2];
    BS2BuzzerSignal signal[3];
} BS2BuzzerAction;

typedef struct {
    uint8_t duration;
    uint8_t reserved[3];
    uint32_t displayID;
    uint32_t resourceId;
} BS2DisplayAction;

typedef struct {
    uint8_t count;
    uint16_t soundIndex;
    uint8_t reserved[5];
} BS2SoundAction;

typedef struct {
    uint32_t deviceID;
    uint8_t type;
    uint8_t stopFlag;
    uint16_t delay;
    union {
        BS2RelayAction relay;
        BS2OutputPortAction outputPort;
        BS2DisplayAction display;
        BS2SoundAction sound;
    }
}
```

```

        BS2LedAction led;
        BS2BuzzerAction buzzer;
    };
} BS2Action;

```

1. *signalID*

2. *count*

3. *onDuration*

on (ms)

4. *offDuration*

off (ms)

5. *delay*

(ms) , count(2),

onDuration(100), offDuration(100), delay(50)

<b>50ms</b>	<b>signal on(100)</b>	<b>signal off(100)</b>	<b>signal on(100)</b>	<b>signal off(100)</b>
-------------	-----------------------	------------------------	-----------------------	------------------------

6. *portIndex*

TTL

7. *reserved*

8. *relayIndex*

Relay

9. *reserved*

10. *color*

LED

0	LED Off
1	LED
2	LED
3	LED
4	LED
5	LED
6	LED
7	LED

11. *reserved*

12. *duration*

LED (ms) .

13. *delay*

LED (ms) .

14. *count*

LED 0 -1

15. *reserved*

16. *tone*

Buzzer ( ) .

0	
1	
2	
3	

17. *count*

Buzzer 0 -1

18. *reserved*

19. *duration*

Display (ms) .

20. *reserved*

Display (ms) .

21. *displayID*

22. *resourceID*

23. *count*

Sound

24. *soundIndex*

Sound resource

0	Welcome sound
1	Auth success sound
2	Auth fail sound

25. *deviceID*

Action

26. *type*

## Action

**[DoorModule-20, CoreStation-40]**

Action type relay TTL(Output) , action 가  
 DM20, CS40 , action type relay action (6)  
 . (TTL 가)

**[DM20]**

- Action type : Relay
- relay.relayIndex : 0 ~ 3 (RELAY 0 ~ 3)
- relay.relayIndex : 4 ~ 9 (OUTPUT 0 ~ 5)

**[CS40]**

- Action type : Relay
- relay.relayIndex : 0 ~ 3 (RELAY 0 ~ 3)
- relay.relayIndex : 4 ~ 11 (OUTPUT 0 ~ 7)

0	None
1	Lock device
2	Unlock device
3	Reboot device
4	Release alarm
5	General input
6	Relay action
7	TTL action
8	Sound action
9	Display action
10	Buzzer action
11	Led action
12	Fire alarm input
13	Auth Success(Access granted)
14	Auth Fail(Access denied)
15	Lift action

## 27. stopFlag

## Action

1 door sensor action 가 action  
 2 action API id 가 ,  
 가 action  
 stopFlag 2 action

0	
1	
2	(V2.6.0 가)

28. *delay*

Action (ms)

## BS2TriggerActionConfig

```
typedef struct {
    uint8_t numItems;
    uint8_t reserved[3];
    BS2TriggerAction items[BS2_MAX_TRIGGER_ACTION];
    uint8_t reserved2[32];
} BS2TriggerActionConfig;
```

1. *numItems*

trigger action

2. *reserved*3. *items*

trigger action 128

4. *reserved2*

## BS2EventConfig

```
typedef struct {
    uint32_t numImageEventFilter;
    struct {
        uint8_t mainEventCode;
        uint8_t reserved[3];
        uint32_t scheduleID;
    } imageEventFilter[BS2_EVENT_MAX_IMAGE_CODE_COUNT];
    uint8_t reserved[32];
} BS2EventConfig;
```

1. *numImageEventFilter*

image log filter

2. *mainEventCode*

image log log main code

3. *reserved*

4. *scheduleID*

image log

5. *reserved*

## BS2WiegandMultiConfig

```
typedef struct {
    uint32_t formatID;
    BS2WiegandFormat format;
    uint8_t reserved[32];
} BS2WiegandInConfig;

typedef struct {
    BS2WiegandInConfig formats[MAX_WIEGAND_IN_COUNT];
    uint8_t reserved[32];
} BS2WiegandMultiConfig;
```

1. *formatID*

WiegandFormat Index

2. *format*

WiegandFormat

3. *reserved*

4. *formats*

WiegandInConfig 15 가

5. *reserved*

## BS1CardConfig

```
typedef struct {
    enum {
        MIFARE_KEY_SIZE = 6,
        MIFARE_MAX_TEMPLATE = 4,

        VALID_MAGIC_NO = 0x1f1f1f1f,
    };

    // Options
    uint32_t magicNo;
    uint32_t disabled;
    uint32_t useCSNOnly;           // default 0
}
```

```
uint32_t      bioentryCompatible; // default 0

// Keys
uint32_t      useSecondaryKey;
uint32_t      reserved1;
uint8_t       primaryKey[MIFARE_KEY_SIZE];
uint8_t       reserved2[2];
uint8_t       secondaryKey[MIFARE_KEY_SIZE];
uint8_t       reserved3[2];

// Layout
uint32_t      cisIndex;
uint32_t      num0fTemplate;
uint32_t      templateSize;
uint32_t      templateStartBlock[MIFARE_MAX_TEMPLATE];

uint32_t      reserve4[15];

} BS1CardConfig;
```

1. *magicNo*

2. *disabled*

flag

3. *useCSNOnly*

CSN

4. *bioentryCompatible*

boientry

5. *useSecondaryKey*

6. *reserved1*

7. *primaryKey*

8. *reserved2*

9. *secondaryKey*

10. *reserved3*

11. *cisIndex*

cis

12. *numOfTemplate*

13. *templateSize*

14. *templateStartBlock*

data storage      start block index

15. *reserved4*

## BS2SystemConfigExt

```
typedef struct {
    uint8_t primarySecureKey[SEC_KEY_SIZE];
    uint8_t secondarySecureKey[SEC_KEY_SIZE];

    uint8_t reserved3[32];
} BS2SystemConfigExt;
```

1. *primarySecureKey*

Master-Slave

2. *secondarySecureKey*

cMaster-Slave

3. *reserved3*

## BS2VoipConfig

```
typedef struct {
    BS2_URL          serverUrl;           ///
    BS2_PORT         serverPort;          ///
    BS2_USER_ID     userID;              ///
    BS2_USER_ID     userPW;             ///

    uint8_t          exitButton;          /// << *, #, 0~9
    uint8_t          dtmfMode;            ///
    BS2_BOOL         bUse;                ///
    uint8_t          reseverd[1];         ///

    uint32_t         numPhonBook;
    BS2UserPhoneItem phonebook[BS2_VOIP_MAX_PHONEBOOK]; ///

    uint8_t          reserved2[32];        ///
}
```

## }` BS2VoipConfig;

### 1. serverUrl

BioStar URL , 256

### 2. serverPort

connectionMode ↗ server mode , BioStar

### 3. userID

### 4. userPW

### 5. exitButton

(\* , # , 0~9)

0	*
1	#
2 ~ 11	0 ~ 9

### 6. dtmfMode

### 7. bUse

### 8. reseverd

### 9. numPhonBook

### 10. phonebook

32

### 8. reserved2

## BS2FaceConfig

```
typedef struct {
    uint8_t      securityLevel;
    uint8_t      lightCondition;
    uint8_t      enrollThreshold;
    uint8_t      detectSensitivity;

    uint16_t     enrollTimeout;
    uint8_t      lfdLevel;
```

```

    bool           quickEnrollment;

    uint8_t        previewOption;
    bool           checkDuplicate;
    uint8_t        operationMode;
    uint8_t        maxRotation;

    // Deprecated
    struct {
        uint16_t   min;
        uint16_t   max;
    } faceWidth;

    // Deprecated
    struct {
        uint16_t   x;
        uint16_t   width;
    } searchRange;

    struct {
        uint8_t    min;          // 30 ~ 100
        uint8_t    max;          // 40 ~ 100, 255
    } detectDistance;           ////< 2 bytes

    BS2_BOOL wideSearch;      ///< 1 byte
    uint8_t unused;

    uint8_t unableToSaveImageOfVisualFace;
    uint8_t reserved[13];
} BS2FaceConfig;

```

### 1. securityLevel

0	
1	
2	

### 2. lightCondition

0	
1	
2	
3	[ + 2.8 ] (FaceStation F2)

### 3. enrollThreshold

0	THRESHOLD_0 ( )
1	THRESHOLD_1
2	THRESHOLD_2
3	THRESHOLD_3
4	THRESHOLD_4 ( )
5	THRESHOLD_5
6	THRESHOLD_6
7	THRESHOLD_7
8	THRESHOLD_8
9	THRESHOLD_9 ( )

#### 4. *detectSensitivity*

0	
1	
2	
3	

#### 5. *enrollTimeout*

FaceStation2, FaceLite : 60

BS2_FACE_ENROLL_TIMEOUT_MIN	30
BS2_FACE_ENROLL_TIMEOUT_MAX	60
BS2_FACE_ENROLL_TIMEOUT_DEFAULT	BS2_FACE_ENROLL_TIMEOUT_MAX

FaceStation F2 : [+ V2.7.1] 20

BS2_FACE_EX_ENROLL_TIMEOUT_MIN	10
BS2_FACE_EX_ENROLL_TIMEOUT_MAX	20
BS2_FACE_EX_ENROLL_TIMEOUT_DEFAULT	BS2_FACE_EX_ENROLL_TIMEOUT_MAX

#### 6. *lfdLevel*

[+ 2.6.3]

FaceStation2, FaceLite : 0  
FaceStation F2 : [+ 2.7.1] 1

0	
1	
2	
3	

#### 7. *quickEnrollment*

[+ 2.6.3]

true

가 1  
false

, false

3

8. *previewOption*

[+ 2.6.3] IR 가 preview  
FaceLite

0	Preview
1	preview , 1/2
2	preview

9. *checkDuplicate*

[+ 2.6.4] true

10. *operationMode*

[+ 2.7.1] FaceStation F2 V1.0.1 가 , Fusion

0	Fusion	Visual matching + IR matching	
1	Visual	Visual matching	
2	Visual + IR	Visual matching, IR	

FaceStation F2 V1.0.1 , BioStatoin 3, BioEntry W3

0	Fusion	Visual matching + IR matching	
1	Fast	Visual matching	

11. *maxRotation*

[+ 2.7.1] FaceStation F2

FaceStation F2 ( )

maxRotation 15

[+ 2.9.6] Angle 가

BS2_MAX_ROTATION_DEFAULT	15
BS2_MAX_ROTATION_ANGLE_15	15
BS2_MAX_ROTATION_ANGLE_30	30
BS2_MAX_ROTATION_ANGLE_45	45
BS2_MAX_ROTATION_ANGLE_60	60
BS2_MAX_ROTATION_ANGLE_75	75
BS2_MAX_ROTATION_ANGLE_90	90
BS2_MAX_ROTATION_ANGLE_MAX	90

12. *faceWidth*

## [+ 2.7.1] FaceStation F2

	(min)	(max)
FSF2	66	250
BS3	130	350
BEW3	130	350

13. *searchRange*

## [+ 2.7.1] FaceStation F2

x (가 ) x

x

	(x)	(width)
FSF2	144	432
BS3	90	540
BEW3	90	540

14. *detectDistance*

## [+ 2.8.3] BioStation 3

[+ 2.9.6] FaceStation F2 BioEntry W3 가.  
faceWidth

( ) cm , 10

	)	(	)	(	)	(	)	(
FSF2	30	130	30	40	130	255	130	
BS3	30	100	30	40	100	255	100	
BEW3	30	100	30	40	100	255	100	

15. *wideSearch*

## [+ 2.8.3] BioStation 3

x width  
(false) searchRange  
, (true)

(true), 가

false

16. *unused*17. *unableToSaveImageOfVisualFace*

## [+ 2.9.6] Visual face

, BS2\_EnrollUserFaceEx API 가 가 가

```
false ,
```

18. reserved

## BS2Rs485ConfigEX

```
typedef struct {
    uint32_t baudRate;
    uint8_t channelIndex;
    uint8_t useResistance;
    uint8_t numOfDevices;
    uint8_t reserved[1];
    BS2Rs485SlaveDeviceEX slaveDevices[BS2_RS485_MAX_SLAVES_PER_CHANNEL];
} BS2Rs485ChannelEX;

typedef struct {
    uint8_t mode[BS2_RS485_MAX_CHANNELS_EX];
    uint8_t numOfChannels;
    uint8_t reserved[2];
    uint8_t reserved1[32];
    BS2Rs485ChannelEX channels[BS2_RS485_MAX_CHANNELS];
} BS2Rs485ConfigEX;
```

1. *baudRate*

RS485

9600
19200
38400
57600
115200

2. *channelIndex*

RS485 network

3. *useResistance*

flag

4. *numOfDevices*

5. *slaveDevices*

32

6. *mode*

RS485

flag

0	
1	Master
2	Slave
3	Standalone

7. *numOfChannels*

RS485

8. *reserved*

9. *reserved1*

10. *channels*

RS485

8

## BS2CardConfigEx

```
typedef struct {
    uint8_t oid_ADF[13];           /// //
//{0x2A,0x85,0x70,0x81,0x1E,0x10,0x00,0x07,0x00,0x00,0x02,0x00,0x00}
    uint8_t size_ADF;             //
    uint8_t reserved1[2];          ///
    uint8_t oid_DataObjectID[8];
    uint16_t size_DataObject[8];
    uint8_t primaryKeyAuth[16];      //
    uint8_t secondaryKeyAuth[16];     /// //
    uint8_t reserved2[24];
} BS2SeosCard;
typedef struct {
    BS2SeosCard seos;
    uint8_t reserved[24];
} BS2CardConfigEx;
```

1. *oid\_ADF*

ADF .( .)

2. *size\_ADF*

ADF size

3. *reserved1*

4. *oid\_DataObjectID*

DataObjectID

5. *size\_DataObject*

DataObject size

6. *primaryKeyAuth*

Seoscard

7. *secondaryKeyAuth*

Seoscard

8. *reserved2*

9. *seos*

BS2SeosCard

10. *reserved*

## BS2DstConfig

```
enum {
    BS2_MAX_DST_SCHEDULE = 2,
};

typedef struct {
    uint16_t year;           // year, 0 means every year.
    uint8_t month;          // [0, 11] : months since January
    int8_t ordinal;         // [0, -1] : first, second, ..., last
    uint8_t weekDay;        // [0, 6] : days since Sunday
    uint8_t hour;           // [0, 23]
    uint8_t minute;         // [0, 59]
    uint8_t second;         // [0, 59]
} BS2WeekTime;

typedef struct {
    BS2WeekTime startTime;
    BS2WeekTime endTime;
    int32_t timeOffset;     // in seconds
    uint8_t reserved[4];
} BS2DstSchedule;

typedef struct {
    uint8_t numSchedules;
    uint8_t reserved[31];
    BS2DstSchedule schedules[BS2_MAX_DST_SCHEDULE];
} BS2DstConfig;
```

1. *year*

, 0

2. *month*

, 0 11 [1 -12 ]

가

3. *ordinal*  
0 ,  
  
4. *weekDay*  
, 0 , 1  
  
5. *hour*  
24  
  
6. *minute*  
  
7. *second*  
  
8. *startTime*  
  
9. *endTime*  
  
10. *timeOffset*  
DST  
1 , 3600  
  
11. *reserved*  
  
12. *numSchedules*  
DST schedule  
  
13. *schedules*  
DST schedule 2

## BS2Configs

```
typedef struct {
    uint32_t configMask;
    BS2FactoryConfig factoryConfig;
    BS2SystemConfig systemConfig;
    BS2AuthConfig authConfig;
    BS2StatusConfig statusConfig;
    BS2DisplayConfig displayConfig;
    BS2IpConfig ipConfig;
    BS2IpConfigExt ipConfigExt;
    BS2TNAConfig tnaConfig;
    BS2CardConfig cardConfig;
    BS2FingerprintConfig fingerprintConfig;
    BS2Rs485Config rs485Config;
    BS2WiegandConfig wiegandConfig;
    BS2WiegandDeviceConfig wiegandDeviceConfig;
```

```

    BS2InputConfig inputConfig;
    BS2WlanConfig wlanConfig;
    BS2TriggerActionConfig triggerActionConfig;
    BS2EventConfig eventConfig;
    BS2WiegandMultiConfig wiegandMultiConfig;
    BS1CardConfig card1xConfig;
    BS2SystemConfigExt systemExtConfig;
    BS2VoipConfig voipConfig;
    BS2FaceConfig faceConfig;
} BS2Configs;

```

### 1. configMask

configuration 가 mask .

0x0000	None
0x0001	Factory configuration
0x0002	System configuration
0x0004	TCP/IP configuration
0x0008	RS485 configuration
0x0010	Wireless LAN configuration
0x0020	Authentication configuration
0x0040	Card configuration
0x0080	Fingerprint configuration
0x0100	Face configuration
0x0200	Trigger Action configuration
0x0400	Display configuration
0x0800	Sound configuration
0x1000	Status Signal(LED, Buzzer) configuration
0x2000	Wiegand configuration
0x4000	USB configuration
0x8000	Time and Attendance configuration
0x10000	Videophone configuration
0x20000	Interphone configuration
0x40000	Voice over IP configuration
0x80000	Input(Supervised input) configuration
0x100000	Wiegand IO Device configuration
0x200000	Time and Attendance configuration
0x400000	DNS and Server url configuration
0x800000	Event configuration
0x1000000	1x Card configuration
0x2000000	Multi-Wiegand configuration
0x4000000	Extended System configuration
0x8000000	<del>Daylight Saving configuration (Deprecated)</del>
0x10000000	RS485 Extended configuration
0x20000000	Extended Card configuration

0x40000000	Daylight Saving configuration
0xFFFFFFFF	All configuration

## BS2IPV6Config

```
enum {
    BS2_MAX_IPV6_ALLOCATED_ADDR = 8,
};

typedef struct {
    uint8_t useIPV6;
    uint8_t reserved1;
    uint8_t useDhcpV6;
    uint8_t useDnsV6;
    uint8_t reserved[1];
    char staticIpAddressV6[BS2_IPV6_ADDR_SIZE];
    char staticGatewayV6[BS2_IPV6_ADDR_SIZE];
    char dnsAddrV6[BS2_IPV6_ADDR_SIZE];
    char serverIpAddressV6[BS2_IPV6_ADDR_SIZE];
    uint16_t serverPortV6;
    uint16_t sslServerPortV6;
    uint16_t portV6;
    uint8_t numOfAllocatedAddressV6;
    uint8_t numOfAllocatedGatewayV6;
    uint8_t reserved[8];
    char
allocatedIpAddressV6[BS2_IPV6_ADDR_SIZE][BS2_MAX_IPV6_ALLOCATED_ADDR];
    char
allocatedGatewayV6[BS2_IPV6_ADDR_SIZE][BS2_MAX_IPV6_ALLOCATED_ADDR];
} BS2IpConfig;
```

1. *useIPV6*  
IP V6 flag
  2. *reserved1*
  3. *useDhcpV6*  
DHCP flag
  4. *useDnsV6*  
server addressss server URL flag
  5. *staticIpAddressV6*  
IP V6
  6. *staticGatewayV6*  
IP V6
  7. *dnsAddrV6*

## DNS V6

8. *serverIpAddressV6*

connectionMode ≠ server mode , BioStar IP V6

9. *serverPortV6*

connectionMode ≠ server mode , BioStar

10. *sslServerPortV6*

connectionMode ≠ server mode , ssl

11. *portV6*

IP V6

12. *numOfAllocatedAddressV6*

IP V6

13. *numOfAllocatedGatewayV6*

IP V6

14. *reserved*15. *allocatedIpAddressV6*

IP V6 . numOfAllocatedAddressV6

16. *allocatedGatewayV6*

IP V6 . numOfAllocatedGatewayV6

**BS2DesFireCardConfigEx**

```

typedef struct {
    uint8_t appMasterKey[16];
    uint8_t fileReadKey[16];
    uint8_t fileWriteKey[16];
    uint8_t fileReadKeyNumber;
    uint8_t fileWriteKeyNumber;
    uint8_t reserved[2];
} BS2DesFireAppLevelKey;                                ///< 52 bytes

typedef struct {
    BS2DesFireAppLevelKey desfireAppKey;      ///< 52 bytes
    uint8_t reserved[16];
} BS2DesFireCardConfigEx;                            ///< 68 bytes

```

1. *appMasterKey*

DesFire application master key

2. *fileReadKey*

key .  
3. *fileWriteKey* key .  
4. *fileReadKeyNumber* key key index .  
5. *fileWriteKeyNumber* key key index .  
6. reserved .  
7. *desfireAppKey*  
DesFire .  
8. reserved .

## BS2AuthConfigExt

```
typedef struct {
    uint32_t extAuthSchedule[BS2_MAX_NUM_OF_EXT_AUTH_MODE];
    uint8_t useGlobalAPB;
    uint8_t globalAPBFailAction;
    uint8_t useGroupMatching;
    uint8_t reserved;

    uint8_t reserved2[4];

    uint8_t usePrivateAuth;
    uint8_t faceDetectionLevel;
    uint8_t useServerMatching;
    uint8_t useFullAccess;

    uint8_t matchTimeout;
    uint8_t authTimeout;
    uint8_t numOperators;
    uint8_t reserved3[1];

    struct {
        char userID[BS2_USER_ID_SIZE];
        uint8_t level;
        uint8_t reserved[3];
    } operators[BS2_MAX_OPERATORS];

    uint8_t reserved4[256];
} BS2AuthConfigExt;
```

1. *extAuthSchedule*

가  
가 ,  
0

11	BS2_EXT_AUTH_MODE_FACE_ONLY	
12	BS2_EXT_AUTH_MODE_FACE_FINGERPRINT	+ + /PIN
13	BS2_EXT_AUTH_MODE_FACE_PIN	+ PIN
14	BS2_EXT_AUTH_MODE_FACE_FINGERPRINT_OR_PIN	+ + /PIN
15	BS2_EXT_AUTH_MODE_FACE_FINGERPRINT_PIN	+ + /PIN
16	BS2_EXT_AUTH_MODE_FINGERPRINT_ONLY	
17	BS2_EXT_AUTH_MODE_FINGERPRINT_FACE	+ + /PIN
18	BS2_EXT_AUTH_MODE_FINGERPRINT_PIN	+ PIN
19	BS2_EXT_AUTH_MODE_FINGERPRINT_FACE_OR_PIN	+ + /PIN
20	BS2_EXT_AUTH_MODE_FINGERPRINT_FACE_PIN	+ + /PIN
21	BS2_EXT_AUTH_MODE_CARD_ONLY	
22	BS2_EXT_AUTH_MODE_CARD_FACE	+ + /PIN
23	BS2_EXT_AUTH_MODE_CARD_FINGERPRINT	+ + /PIN
24	BS2_EXT_AUTH_MODE_CARD_PIN	+ PIN
25	BS2_EXT_AUTH_MODE_CARD_FACE_OR_FINGERPRINT	+ + /PIN
26	BS2_EXT_AUTH_MODE_CARD_FACE_OR_PIN	+ + /PIN
27	BS2_EXT_AUTH_MODE_CARD_FINGERPRINT_OR_PIN	+ + /PIN
28	BS2_EXT_AUTH_MODE_CARD_FACE_OR_FINGERPRINT_OR_PIN	+ + /PIN
29	BS2_EXT_AUTH_MODE_CARD_FACE_FINGERPRINT	+ + /PIN
30	BS2_EXT_AUTH_MODE_CARD_FACE_PIN	+ + PIN
31	BS2_EXT_AUTH_MODE_CARD_FINGERPRINT_FACE	+ + /PIN
32	BS2_EXT_AUTH_MODE_CARD_FINGERPRINT_PIN	+ + PIN
33	BS2_EXT_AUTH_MODE_CARD_FACE_OR_FINGERPRINT_PIN	+ + /PIN
34	BS2_EXT_AUTH_MODE_CARD_FACE_FINGERPRINT_OR_PIN	+ + /PIN
35	BS2_EXT_AUTH_MODE_CARD_FINGERPRINT_FACE_OR_PIN	+ + /PIN
36	BS2_EXT_AUTH_MODE_ID_FACE	ID + ID + /PIN
37	BS2_EXT_AUTH_MODE_ID_FINGERPRINT	ID + ID + /PIN
38	BS2_EXT_AUTH_MODE_ID_PIN	ID + PIN
39	BS2_EXT_AUTH_MODE_ID_FACE_OR_FINGERPRINT	ID + ID + /PIN
40	BS2_EXT_AUTH_MODE_ID_FACE_OR_PIN	ID + ID + /PIN
41	BS2_EXT_AUTH_MODE_ID_FINGERPRINT_OR_PIN	ID + ID + /PIN

42	BS2_EXT_AUTH_MODE_ID_FACE_OR_FINGERPRINT_OR_PIN	ID + / /PIN
43	BS2_EXT_AUTH_MODE_ID_FACE_FINGERPRINT	ID + +
44	BS2_EXT_AUTH_MODE_ID_FACE_PIN	ID + + PIN
45	BS2_EXT_AUTH_MODE_ID_FINGERPRINT_FACE	ID + +
46	BS2_EXT_AUTH_MODE_ID_FINGERPRINT_PIN	ID + + PIN
47	BS2_EXT_AUTH_MODE_ID_FACE_OR_FINGERPRINT_PIN	ID + / + PIN
48	BS2_EXT_AUTH_MODE_ID_FACE_FINGERPRINT_OR_PIN	ID + + /PIN
49	BS2_EXT_AUTH_MODE_ID_FINGERPRINT_FACE_OR_PIN	ID + + /PIN

2. *useGlobalAPB*

flag

3. *globalAPBFailAction*

BioStar

0	APB
1	Soft APB
2	Hard APB

4. *useGroupMatching*

flag

5. *reserved*6. *reserved2*7. *usePrivateAuth*

flag

8. *faceDetectionLevel*

A2

Normal/Strict

0

가

,

가

0	
1	Normal mode
2	Strict mode

A2	가	, FaceStation2	FaceLite
----	---	----------------	----------

9. *useServerMatching*

Matching server

flag

10. *useFullAccess*

11. *matchTimeout*

(sec)

12. *authTimeout*

(sec)

13. *numOperators*

operator

14. *reserved3*

15. *userID*

16. *level*

가

0	
1	
2	
3	

Operator	가	,	가	operator	<b>numOperators</b>
----------	---	---	---	----------	---------------------

17. *reserved*

18. *reserved4*

## BS2FaceConfigExt

```
typedef struct {
    uint8_t thermalCheckMode;
```

```

    uint8_t maskCheckMode;
    uint8_t reserved[2];

    uint8_t thermalFormat;
    uint8_t reserved2;

    uint16_t thermalThresholdLow;
    uint16_t thermalThresholdHigh;
    uint8_t maskDetectionLevel;
    uint8_t auditTemperature;

    uint8_t useRejectSound;
    uint8_t useOverlapThermal;
    uint8_t useDynamicROI;
    uint8_t faceCheckOrder;
} BS2FaceConfigExt;

```

### 1. *thermalCheckMode*

HARD , thermalThreshold  
 SOFT , thermalThreshold

thermalCheckMode가 (0),  
 thermalFormat, thermalThreshold, auditTemperature, useOverlapThermal  
 useRejectSound sound , faceCheckOrder

0		
1	(HARD)	
2	(SOFT)	

### 2. *maskCheckMode*

FaceStation F2

FaceStation 2

HARD , maskDetectionLevel  
 SOFT , maskDetectionLevel

maskCheckMode가 (0),  
 maskDetectionLevel  
 useRejectSound sound , faceCheckOrder 가

0		
1	(HARD)	
2	(SOFT)	

### 3. *reserved*

### 4. *thermalFormat*

0		
1		

5. reserved2

6. *thermalThresholdLow*

: FaceStation F2 V1.0.2, FaceStation 2 V1.5.0  
100

가 , 100 (1°) 4500 (45°)  
3200 (32°) , 3200 (32°)  
thermalThresholdHigh

7. *thermalThresholdHigh*

, 100  
가 , 100 (1°) 4500 (45°)  
3800(38°) , 3800 (38°)  
thermalThresholdLow

8. *maskDetectionLevel*

FaceStation F2

FaceStation 2

0		
1		
2		
3		

9. *auditTemperature*

10. *useRejectSound*

thermalThreshold maskDetectionLevel

11. *useOverlapThermal*

12. *useDynamicROI*

true

13. *faceCheckOrder*

ID , PIN , , ,

0		
1		
2		

## BS2ThermalCameraConfig

```
typedef struct {
    uint8_t distance;
    uint8_t emissionRate;

    struct {
        uint16_t x;
        uint16_t y;
        uint16_t width;
        uint16_t height;
    } roi;

    uint8_t useBodyCompensation;
    int8_t compensationTemperature;
} BS2ThermalCameraConfig;
```

1. *distance*

cm

100

2. *emissionRate*

가

[95/97/98]

가

98

3. *roi*

ROI(Region of interest)

(x, y) , (width, height)

4. *useBodyCompensation*

5. *compensationTemperature*

가

10

-50

50

## BS2BarcodeConfig

```
typedef struct {
    uint8_t useBarcode;
    uint8_t scanTimeout;
```

```

    uint8_t bypassData;
    uint8_t treatAsCSN;

    uint8_t useVisualBarcode;
    uint8_t motionSensitivity;
    uint8_t visualCameraScanTimeout;
    uint8_t reserved[9];
} BS2BarcodeConfig;

```

1. *useBarcode*

XS2-QR      Barcode      flag

2. *scanTimeout*Barcode scan  
4      , 4~10      가

4	BS2_BARCODE_TIMEOUT_DEFAULT	
4	BS2_BARCODE_TIMEOUT_MIN	
10	BS2_BARCODE_TIMEOUT_MAX	

3. *bypassData*[+2.8.2]      barcode      ,  
32 byte      (BS2CSNCARD data      )      ,  
[BS2\\_SetBarcodeScanListener](#)      ,      512 byte      barcode4. *treatAsCSN*[+2.8.2] Barcode      CSN  
XS2-QR 1.1.3      , false      ,  
Barcode      ASCII code 32      126  
([BS2\\_WriteQRCode](#)      )  
true      , barcode      CSN  
,      ,      가      barcode  
, card type      , CSN      barcode5. *useVisualBarcode*

[+ 2.9.1] Visual barcode      flag

XS2-Finger	V1.2.0
XS2-Card	V1.2.0
BS3	V1.1.0

Visual barcode      QR code sensor 가      ,      visual camera      QR code  
,  
[BS2\\_EnableDeviceLicense](#)

## 6. *motionSensitivity*

[+ 2.9.1] Visual barcode ,

0	BS2_MOTION_SENSITIVITY_LOW	
1	BS2_MOTION_SENSITIVITY_NORMAL	
2	BS2_MOTION_SENSITIVITY_HIGH	

## 7. *visualCameraScanTimeout*

[+ 2.9.1] Visual camera scan

10 , 3~20 가

10	BS2_VISUAL_BARCODE_TIMEOUT_DEFAULT	
3	BS2_VISUAL_BARCODE_TIMEOUT_MIN	
20	BS2_VISUAL_BARCODE_TIMEOUT_MAX	

## 8. reserved

## **BS2InputConfigEx**

```

typedef struct {
    uint8_t    numInputs;
    uint8_t    numSupervised;
    uint8_t    reserved[18];

    struct {
        uint8_t    portIndex;
        uint8_t    switchType;
        uint16_t   duration;

        uint8_t    reserved;
        uint8_t    supervisedResistor;
        uint8_t    reserved1[16];

        uint8_t    reserved2[26];
    } inputs[BS2_MAX_INPUT_NUM_EX];

    uint8_t    reserved2[200];
} BS2InputConfigEx;

```

## 1. *numInputs*

**Input****2. numSupervised**

supervised input

**3. reserved****4. portIndex****Input****5. switchType****Input**

0	Normally Open
1	Normally Closed

**6. duration**

Input (ms)

**7. reserved****8. supervisedResistor**

Supervised input , (unsupervised)

0	1K
1	2.2K
2	4.7K
3	10K
254	Unsupervised( )

**9. reserved1****10. reserved2****11. reserved2****BS2RelayActionConfig**

```

typedef struct {
    uint32_t          deviceID;           ///< 4 bytes
    uint8_t          reserved[16];        ///< 16 bytes

    struct {

```

```

        uint8_t      port;           ///< 1 byte (relay port)
        uint8_t      reserved0;     ///< 1 byte
        uint8_t      disconnEnabled; ///< 1 byte (RS485
disconnection)
        uint8_t      reserved[9];    ///< 9 bytes

    struct {
        uint8_t      port;           ///< 1 byte (input port)
        uint8_t      type;          ///< 1 byte (linkage/latching/release)
        uint8_t      mask;          ///< 1 byte (alarm/fault)
        uint8_t      reserved[9];    ///< 9 bytes
    } input[BS2_MAX_RELAY_ACTION_INPUT];   ///< 192 bytes
} relay[BS2_MAX_RELAY_ACTION];           ///< 816 bytes

        uint8_t      reserved2[152];   ///< 152 bytes
} BS2RelayActionConfig;

```

1. *deviceID*

2. *reserved*

3. *relay*

Relay

4. *port*

Relay port

5. *reserved0*

6. *disconnEnabled*

true , RS485

7. *reserved*

8. *input*

relay port 가 input port

9. *port*

Input port

10. *type*

input	input	
Linkage	mask	alarm

<b>type</b>			
NONE	0		
LINKAGE	1	input	relay
LATCHING	2		

<b>type</b>		
RELEASE	3	

11. *mask*

Input mask

<b>type</b>		
NONE	0	
ALARM	1	
FAULT	2	/

12. *reserved*13. *reserved2***BS2VoipConfigExt**

```

typedef struct {
    BS2_USER_ID phoneNumber;
    char description[48 * 3];

    uint8_t reserved[32];
} BS2ExtensionNumber;

typedef struct {
    BS2_BOOL enabled;
    BS2_BOOL useOutboundProxy;
    uint16_t registrationDuration;

    BS2_URL address;
    BS2_PORT port;

    struct {
        uint8_t speaker;           // 0 ~ 100
        uint8_t mic;              // 0 ~ 100
    } volume;                  ///< 2 bytes

    BS2_USER_ID id;
    BS2_USER_ID password;
    BS2_USER_ID authorizationCode;

    struct {
        BS2_URL address;
        BS2_PORT port;
        uint8_t reserved[2];
    } outboundProxy;
}

```

```
    uint8_t exitButton;           /// *, #, 0~9
    uint8_t reserved1;
    uint8_t numPhoneBook;
    BS2_BOOL showExtensionNumber;

    BS2ExtensionNumber phonebook[128];

    uint8_t reserved2[32];       ///< 32 bytes (reserved)
} BS2VoipConfigExt;
```

1. *phoneNumber*

2. *description*

3. *reserved*

4. *enabled*

VoIP extension

5. *useOutboundProxy*

Outbound

6. *registrationDuration*

SIP

, 60~600

7. *address*

SIP ( BioStar) IP

8. *port*

SIP 5060

9. *speaker*

0 100 50

10. *mic*

0 100 50

11. *id*

SIP ID

12. *password*

SIP

13. *authorizationCode*

SIP

14. *outboundProxy*

Outbound

15. *address*

Outbound IP

16. *port*  
Outbound

17. *reserved*

18. *exitButton*

*	'*' ASCII code 42
#	'#' ASCII code 35
0~9	'0'~'9' ASCII code (48~57)

19. *reserved1*

20. *numPhoneBook*

21. *showExtensionNumber*

22. *phonebook*  
128

23. *reserved2*

## BS2RtspConfig

```
typedef struct {
    BS2_USER_ID id;
    BS2_USER_ID password;

    BS2_URL address;

    BS2_PORT port;
    BS2_BOOL enabled;
    uint8_t reserved;

    uint8_t reserved2[32];
} BS2RtspConfig;
```

1. *id*  
RTSP

2. *password*  
RTSP

3. *address*

RTSP

4. port

RTSP

554

5. enabled

RTSP

6. reserved

7. reserved2

## BS2License

```
typedef struct {
    uint8_t index;
    uint8_t hasCapability;
    uint8_t enable;
    uint8_t reserved;
    BS2_LICENSE_TYPE licenseType;
    BS2_LICENSE_SUB_TYPE licenseSubType;
    uint32_t enableTime;
    uint32_t expiredTime;
    uint32_t issueNumber;
    uint8_t name[BS2_USER_ID_SIZE];
} BS2License;
```

1. index

2. hasCapability

가

1

3. enable

가

4. reserved

5. licenseType

0x0000	None
0x0001	Visual QR

6. licenseSubType

licenseType

0	None
1	Visual QR (CodeCorp)

7. *enableTime*  
, POSIX time

8. *expiredTime*  
, 0

9. *issueNumber*

10. *name*

## BS2LicenseConfig

```
typedef struct {
    uint8_t          version;
    uint8_t          numOfLicense;
    uint8_t          reserved[2];
    BS2License      license[BS2_MAX_LICENSE_COUNT];
    uint8_t          reserved1[16];
} BS2LicenseConfig;
```

1. *version*

2. *numOfLicense*

3. *reserved*

4. *license*  
, 16

5. *reserved1*

## BS2BarcodeConfig

```
typedef struct {
    uint8_t  useBarcode;
    uint8_t  scanTimeout;
    uint8_t  bypassData;
    uint8_t  treatAsCSN;
```

```

    uint8_t useVisualBarcode;
    uint8_t motionSensitivity;
    uint8_t visualCameraScanTimeout;
    uint8_t reserved[9];
} BS2BarcodeConfig;

```

#### 1. useBarcode

XS2-QR      Barcode      flag

#### 2. scanTimeout

Barcode scan

4      , 4~10      가

4	BS2_BARCODE_TIMEOUT_DEFAULT	
4	BS2_BARCODE_TIMEOUT_MIN	
10	BS2_BARCODE_TIMEOUT_MAX	

#### 3. bypassData

[+2.8.2]      barcode      ,  
                   barcode  
 32 byte      (BS2CSNCARD data      )      ,  
[BS2\\_SetBarcodeScanListener](#)      ,      512 byte      barcode

#### 4. treatAsCSN

[+2.8.2] Barcode      CSN  
 XS2-QR 1.1.3      , false      ,  
                   barcode      ASCII code 32      126  
 ([BS2\\_WriteQRCode](#)      )  
 true      , barcode      CSN  
                   ,      가      barcode  
                   , card type      , CSN      barcode

#### 5. useVisualBarcode

[+ 2.9.1] Visual barcode      flag

XS2-Finger	V1.2.0
XS2-Card	V1.2.0
BS3	V1.1.0

Visual barcode      QR code sensor가      ,      visual camera      QR code  
                   ,      가  
[BS2\\_EnableDeviceLicense](#)

#### 6. motionSensitivity

[+ 2.9.1] Visual barcode      ,

0	BS2_MOTION_SENSITIVITY_LOW	
1	BS2_MOTION_SENSITIVITY_NORMAL	
2	BS2_MOTION_SENSITIVITY_HIGH	

### 7. visualCameraScanTimeout

[+ 2.9.1] Visual camera scan  
10 , 3~20

가

10	BS2_VISUAL_BARCODE_TIMEOUT_DEFAULT	
3	BS2_VISUAL_BARCODE_TIMEOUT_MIN	
20	BS2_VISUAL_BARCODE_TIMEOUT_MAX	

### 8. reserved

## BS2OsdpStandardConfig

```

typedef struct {
    uint32_t          baudRate;           ///< 4 bytes
    uint8_t           channelIndex;        ///< 1 byte
    uint8_t           useResistance;       ///< 1 byte
    uint8_t           numDevices;          ///< 1 byte
    BS2_OSDP_CHANNEL_TYPE   channelType;  ///< 1 byte
    BS20sdpStandardDevice
slaveDevices[BS2_RS485_MAX_SLAVES_PER_CHANNEL];  // 28 * 32 = 896 bytes
    uint8_t           reserved[4];          ///< 4 bytes
} BS20sdpStandardChannel;                         ///< 908 bytes

typedef struct {
    uint8_t           mode[BS2_RS485_MAX_CHANNELS_EX];  ///< 8 byte
    uint16_t          numChannels;          ///< 2 byte
    uint8_t           reserved[2];          ///< 2 bytes
    (packing)
    uint8_t           reserved1[32];         ///< 32 bytes
    (reserved)
    BS20sdpStandardChannel channels[BS2_RS485_MAX_CHANNELS_EX];  // 908 * 8 bytes = 7264 bytes
} BS20sdpStandardConfig;                          ///< 7308 bytes

```

### 1. baudRate

OSDP

9600
19200
38400
57600
115200

**2. channelIndex**

OSDP 가 RS485

**3. useResistance**

flag

**4. numOfDevices****5. channelType**

RS485	가					
CoreStation40	,	가	0~4	5	,	
OSDP	가	가	, Suprema	, OSDP		0
channelType	1	Suprema	가	,	Suprema	,
		OSDP	가	,	OSDP	, channelType
2		Suprema	가			
CoreStation40			Suprema	, OSDP		
OSDP	가		가		2	
		channelType	3		가	

0	Normal
1	Suprema
2	OSDP
3	OSDP FULL

**6. slaveDevices****7. reserved****8. mode**

RS485	flag		
Osdp standard config	CoreStation40	2023/1/12	master

0	
1	Master
2	Slave

3	Standalone ( )

9. *numOfChannels*

CoreStation40 5

10. *reserved*11. *reserved1*12. *channels*

OSDP				
8	가	, CoreStation40	5	가 0~4

**BS2OsdpStandardActionConfig**

```

typedef struct{
    BS2_BOOL                                use;           ///< 1 byte
    uint8_t                                 readerNumber;  ///< 1 byte
    uint8_t                                 ledNumber;     ///< 1 byte

    BS2_OSDP_STANDARD_LED_COMMAND          tempCommand;   ///< 1 byte
    uint8_t                                 tempOnTime;    ///< 1 byte
    uint8_t                                 tempOffTime;   ///< 1 byte
    BS2_OSDP_STANDARD_COLOR               tempOnColor;   ///< 1 byte
    BS2_OSDP_STANDARD_COLOR               tempOffColor;  ///< 1 byte
    uint16_t                               tempRunTime;   ///< 2 bytes

    BS2_OSDP_STANDARD_LED_COMMAND          permCommand;   ///< 1 byte
    uint8_t                                 permOnTime;    ///< 1 byte
    uint8_t                                 permOffTime;   ///< 1 byte
    BS2_OSDP_STANDARD_COLOR               permOnColor;   ///< 1 byte
    BS2_OSDP_STANDARD_COLOR               permOffColor;  ///< 1 byte

    uint8_t                               reserved;      ///< 1 byte
} BS2OsdpStandardLedAction;                ///< 16 bytes

typedef struct {
    BS2_BOOL                                use;           ///< 1 byte
    uint8_t                                 readerNumber;  ///< 1 byte
    BS2_OSDP_STANDARD_TONE                 tone;          ///< 1 byte
    uint8_t                                 onTime;        ///< 1 byte
    uint8_t                                 offTime;       ///< 1 byte
    uint8_t                                 numOfCycle;    ///< 1 byte
    uint8_t[2]                             reserved[2];  ///< 2 bytes
} BS2OsdpStandardBuzzerAction;             ///< 8 bytes

```

```

typedef struct {
    BS2 OSDP_STANDARD_ACTION_TYPE   actionTypes;      ///< 1 byte
    uint8_t                         reserved[3];     ///< 3 bytes
    BS20sdpStandardLedAction        led[2];          ///< 16 x 2 = 32 bytes
    BS20sdpStandardBuzzerAction    buzzer;          ///< 8 bytes
} BS20sdpStandardAction;

typedef struct
{
    uint8_t                      version;           ///< 1 byte
    uint8_t                      reserved[3];       ///< 3 bytes
    BS20sdpStandardAction        actions[BS2 OSDP_STANDARD_ACTION_MAX_COUNT];
///< 44 x 32 = 1408
} BS20sdpStandardActionConfig;                   ///< 1412 bytes

```

## 1. use

LED action

## 2. readerNumber

OSDP

## 3. ledNumber

OSDP 가 LED

## 4. tempCommand

Temporary command

0	No Operation
1	Cancel
2	Set

## 5. tempOnTime

Temporary command LED 가 , 100ms  
2 LED on 20

## 6. tempOffTime

Temporary command LED 가 , 100ms  
1 LED off 10

## 7. tempOnColor

Temporary command On LED

0	BLACK
1	RED
2	GREEN
3	AMBER
4	BLUE
5	MAGENTA

6	CYAN
7	WHITE

**8. *tempOffColor***

Temporary command      Off      LED

0	BLACK
1	RED
2	GREEN
3	AMBER
4	BLUE
5	MAGENTA
6	CYAN
7	WHITE

**9. *tempRunTime***Temporary command      LED On/Off      100ms  
tempOnTime/tempOffTime, tempOnColor/tempOffColor  
tempRunTime**10. *permCommand***Permanent command      . 11. *permOnTime*      LED가 , 100ms  
Permanent command      LED가**12. *permOffTime***

Permanent command      LED가 , 100ms

**13. *permOnColor***

Permanent command      On      LED

**14. *permOffColor***

Permanent command      Off      LED

**15. *reserved*****16. *use***

tone action

**17. *readerNumber* OSDP****18. *tone***

Buzzer

0	None
1	Off
2	On

19. *onTime*

tone      On      100ms

20. *offTime*

tone      Off      100ms

21. *numOfCycle*

tone On/Off      0

22. *reserved*23. *actionType*

action

0	None
1	Success
2	Fail
3	Wait input

24. *reserved*25. *led*

OSDP      LED

26. *buzzer*

OSDP      buzzer

27. *version*

Action configuration      0

28. *reserved*29. *actions*

OSDP      LED/buzzer      ,      32

**BS2CustomMifareCard**

```
typedef struct {
    uint8_t primaryKey[6];
    uint8_t reserved1[2];
    uint8_t secondaryKey[6];
    uint8_t reserved2[2];
    uint16_t startBlockIndex;
    uint8_t dataSize;
    uint8_t skipBytes;
    uint8_t reserved[4];
}
```

### }` BS2CustomMifareCard;

1. *primaryKey*

Mifare card

2. *reserved1*

3. *secondaryKey*

Mifare card

4. *reserved2*

5. *startBlockIndex*

Mifare data storage

start block index

6. *dataSize*

가 byte

7. *skipBytes*

가

0

, byte

8. *reserved*

## BS2CustomDesFireCard

```
typedef struct {
    uint8_t primaryKey[16];
    uint8_t secondaryKey[16];
    uint8_t appID[3];
    uint8_t fileID;
    uint8_t encryptionType;           // 0: DES/3DES, 1: AES
    uint8_t operationMode;           // 0: legacy(use picc master
key), 1: new mode(use app master, file read, file write key)
    uint8_t dataSize;
    uint8_t skipBytes;
    uint8_t reserved[4];
    BS2DesFireAppLevelKey desfireAppKey; // <52 bytes
} BS2CustomDesFireCard;               // <96 Bytes
```

1. *primaryKey*

DesFire card

. ( )

2. *secondaryKey*

DesFire card

. ( )

3. *appID*

## DESFire

4. *fileID*

DESFire

5. *encryptionType*

0	DES/3DES
1	AES

6. *operationMode*

0	(PICC master key )
1	(App master key )

7. *dataSize*

가 byte

8. *skipBytes*

가 0 , byte

9. *reserved*10. *desfireAppKey*

DesFire card ( )

**BS2CustomCardConfig**

```

typedef struct {
    BS2_CARD_DATA_TYPE dataType;
    BS2_BOOL useSecondaryKey;
    uint8_t reserved1[2];

    BS2CustomMifareCard mifare;
    BS2CustomDesFireCard desfire;
    uint8_t reserved2[24];
    uint8_t reserved3[96];

    BS2_CARD_BYTE_ORDER smartCardByteOrder;
    uint8_t reserved4[3];
    BS2_UID formatID;
    uint8_t reserved5[8];

```

## }` BS2CustomCardConfig;

### 1. dataType

Card

0	
1	
2	UTF16
3	BCD

### 2. useSecondaryKey

flag

### 3. reserved1

### 4. mifare

Mifare custom card

### 5. desfire

DESFire custom card

### 6. reserved2

### 7. reserved3

### 8. smartCardByteOrder

MSB      LSB

0	MSB
1	LSB

### 9. reserved4

### 10. formatID

BioStar 2

card configuration

가

### 11. reserved5

1)

, Maximum Transmission Unit

2)

, Most Significant Bit

3)

, Least Significant Bit

From:

<http://kb.supremainc.com/bs2sdk/> - **BioStar 2 Device SDK**

Permanent link:

[http://kb.supremainc.com/bs2sdk/doku.php?id=ko:configuration\\_api](http://kb.supremainc.com/bs2sdk/doku.php?id=ko:configuration_api)

Last update: **2024/04/04 13:53**