

Door Control API	1
.....	1
BS2DoorRelay	1
BS2DoorSensor	1
BS2ExitButton	2
BS2DoorStatus	2
BS2Door	4

Door Control API

가 , 가 , ..

- [BS2_GetDoor:](#) 가 .
- [BS2_GetAllDoor:](#) 가 .
- [BS2_GetDoorStatus:](#) 가 .
- [BS2_GetAllDoorStatus:](#) 가 .
- [BS2_SetDoor:](#) .
- [BS2_SetDoorAlarm:](#) .
- [BS2_RemoveDoor:](#) .
- [BS2_RemoveAllDoor:](#) .
- [BS2_ReleaseDoor:](#) .
- [BS2_LockDoor:](#) ,
- [BS2_UnlockDoor:](#) ,

BS2DoorRelay

```
typedef struct {
    uint32_t deviceID;
    uint8_t port;
    uint8_t reserved[3];
} BS2DoorRelay;
```

1. *deviceID*

2. *port*

port number

3. *reserved*

BS2DoorSensor

```
typedef struct {
    uint32_t deviceID;
    uint8_t port;
    uint8_t switchType;
    uint8_t apbUseDoorSensor;
    uint8_t reserved[1];
}
```

```
} BS2DoorSensor;
```

- 1. *deviceId*
- 2. *port*
port number
- 3. *switchType*

0	
1	

- 4. *apbUseDoorSensor*
APB door sensor
- 5. *reserved*

BS2ExitButton

```
typedef struct {  
    uint32_t deviceId;  
    uint8_t port;  
    uint8_t switchType;  
    uint8_t reserved[2];  
} BS2ExitButton ;
```

- 1. *deviceId*
- 2. *port*
port number
- 3. *switchType*

0	
1	

- 4. *reserved*

BS2DoorStatus

```
typedef struct {
```

```
uint32_t id;
uint8_t opened;
uint8_t unlocked;
uint8_t heldOpened;
uint8_t unlockFlags;
uint8_t lockFlags;
uint8_t alarmFlags;
uint8_t reserved[2];
uint32_t lastOpenTime;
} BS2DoorStatus;
```

1. *id*

2. *opened*

flag .

3. *unlocked*

flag .

4. *heldOpened*

flag .

5. *unlockFlags*

(OPERATOR),
unlockFlags lockFlags (NONE) 가

0		
1		
4		
2		

6. *lockFlags*

0		
1		
4		
2		

7. *alarmFlags*

0	
1	

4	
2	APB

8. reserved
9. lastOpenTime

BS2Door

```
typedef struct {
    uint32_t doorID;
    char name[BS2_MAX_DOOR_NAME_LEN];
    uint32_t entryDeviceID;
    uint32_t exitDeviceID;
    BS2DoorRelay relay;
    BS2DoorSensor sensor;
    BS2ExitButton button;
    uint32_t autoLockTimeout;
    uint32_t heldOpenTimeout;
    uint8_t instantLock;
    uint8_t unlockFlags;
    uint8_t lockFlags;
    uint8_t unconditionalLock;
    BS2Action forcedOpenAlarm[BS2_MAX_FORCED_OPEN_ALARM_ACTION];
    BS2Action heldOpenAlarm[BS2_MAX_HELD_OPEN_ALARM_ACTION];
    uint32_t dualAuthScheduleID;
    uint8_t dualAuthDevice;
    uint8_t dualAuthApprovalType;
    uint32_t dualAuthTimeout;
    uint8_t numDualAuthApprovalGroups;
    uint8_t reserved2[1];
    uint32_t dualAuthApprovalGroupID[BS2_MAX_DUAL_AUTH_APPROVAL_GROUP];
    BS2AntiPassbackZone apbZone;
} BS2Door;
```

1. doorID

. 165535
2. name

BioStar. 1가
3. entryDeviceID
4. exitDeviceID

5. relay

6. sensor

/

7. button

Exit

8. autoLockTimeout

9. heldOpenTimeout

10. instantLock

가

flag

11. unlockFlags

(OPERATOR),

unlockFlags

lockFlags

(NONE)

가

0		
1		
4		
2		

12. lockFlags

0		
1		
4		
2		

13. unconditionalLock

autoLock timeout

door lock

flag

0	autoLock timeout door close door lock . (door open door가 close)
1	autoLock timeout door open/close door lock

14. forcedOpenAlarm

15. *heldOpenAlarm*

5 .

16. *dualAuthScheduleID*

0 , 1 ,

17. *dualAuthDevice*

가 flag .

0	
1	
2	
3	

18. *dualAuthApprovalType*

가 flag

0	
1	

19. *dualAuthTimeout*

1 2 .

20. *numDualAuthApprovalGroups*

가 .

21. *reserved2*

.

22. *dualAuthApprovalGroupID*

가 16 .

23. *apbZone*

가 . [Zone Control API](#) .

From:
<http://kb.supremainc.com/bs2sdk/> - **BioStar Device SDK**

Permanent link:
http://kb.supremainc.com/bs2sdk/doku.php?id=ko:door_control_api&rev=1734391931

Last update: **2024/12/17 08:32**