Table of Contents

How to Upgrade the Resource Firmware for BioLite Net V2	1
Overview	1
Preparations	1
Start BioStar 2 and update the resource firmware	1

1/3

How to Upgrade the Resource Firmware for BioLite Net V2

Overview

Sometimes if you complete the device firmware update for the BioLite Net v2, the device menu and its associated string item does not correspond to each other. This problem can be introduced when the firmware update presented some enhancement/modification in the device functionality/menu items and the existing resource firmware do not reflect the changes.

In this case, you also have to upgrade the resource firmware to maintain the up-to-date status.

Preparations

1. Make sure you have the resource firmware placed in the path C:\Program Files (x86)\BioStar 2\resource.

2. Have a BioLite Net device added on the BioStar 2.

Start BioStar 2 and update the resource firmware

- 1. Start BioStar2 client and log in.
- 2. Go to **DEVICE** and click the BioLite Net device that you want to update its resource firmware.
- 3. Expand the **Advanced** tab and locate the **Display/Sound** section.

BioStar 2	🚯 Setting 🕧 About 🦁 Help					Administrator E Lagout
	Time Zone System Display Date	(UTC+9:00) Secol, Tokyo, Oxeka, Sep 2015/13/29	porn, Yakufsk	*	Oct Time Bot Time	
	Authentication					
	 Auth Mode Full Access Fingerprint Scan Timeout 	Citadie	Always Always Always	29 29 29	Auth Teneout 10 ave Sensar Sanativity	
	Template Format Card ID Format	Suprena			Matching Timeout	
	* Layout	Note		*		
	Advanced					colu
	Advanced				A	:ply Cancel

2021/03/11 18:46	2/3						How t	o Upgrade the Resou	urce Firmwai	re for BioLite Net V2
3	Code 2									
DATE: BOARD	Code 3									
A usin	Code 4									
evvot Display/Sound										
• Language	English	w Upd	ate Resource							
• Volume	CN CN						Menu Timeout	— • ×) see	
Backlight Tir	neout	20 846					Mog. Timeout		D sec	
20ME LED/Buzzer	Event									
\oplus	Normal	+ LED	infinite 🔍	01						
ACCESS CONTROL	Locked		BLUE	* 2000	msec 0	msec				
27	RTC Error		CYAN	* 2000	msec 0	maec				
MONTENNE	Waiting Input		OFF	w 0	mses 0	msec				
	Waiting DHCP	Buzzer	Infinite 🔾) orr	Counts	0				
\odot	Scan Finger		OFF	* 0	mues 0	maec	Fade Out			
ATTEMANOE	Scan Card		OFF		msec 0	mset	Fade Out			
	Auth Success		055				C Facto Cast			
	Auth Fail		UFF	-	man []		- Page out			
	Auth Duress									

4. Please click **Update Resource** button next to the **Language** menu item.

 Language 	English	- U	pdate Resource	<u>e</u>
Volume	ON			Menu Timout 20 sec
Backlight Timeout	-	20 545		Msg. Timeout 2.0 seo
LED/Buzzer	Event			
	Normal	• LED	Infinite	ΟΝ
	Locked		BLUE	v 2000 msec 0 msec
	RTC Error		CYAN	* 2000 msec 0 msec
	Waiting Input		OFF	v 0 msec 0 msec
	Waiting DHCP	Duzzer	Infinite	OFF Counts 0
	Scan Finger		OFF	v 0 msec 0 msec Fode Out
	Scan Card		OFF	V 0 msec 0 msec Fade Out
	Auth Success		OFF	O msec O msec Fade Out
	Auth Fail		511	
	Auth Duress			

5. On **Language Resource** window, please select the appropriate Resource file to update the device resource.

Language Resource	×
BioLiteNet 538101263	
Device Type	Resource File
BioLiteNet	bln_res.2.1.2.bin
BioLiteNet	BLN_RES.2.2.0.bin

6. Please verify that the device menu item and its associated string corresponds to each other.

From: http://kb.supremainc.com/knowledge/ -

Permanent link: http://kb.supremainc.com/knowledge/doku.php?id=en:2xfaq_how_to_upgrade_the_resource_firmware_for_bln_v2

Last update: 2020/01/02 17:03