

# Table of Contents

<b>BS2_ClearLog</b> .....	1
Declaration .....	1
Parameter .....	1
Return Value .....	1
See Also .....	1

[Log Management API](#) > [BS2\\_ClearLog](#)

---

## BS2\_ClearLog

Deletes all logs.

id values(refer to [BS2Event](#), [BS2EventBlob](#)) which are internally managed after calling functions are not initialized or changed.

Newly generated log id will be +1 to the previous id value.

id can be increased up to 0xFFFFFFFF(maximum value of uint32\_t) and then it will be increased from 0 again.

### Declaration

```
#include "BS_API.h"
int BS2_ClearLog(void* context, uint32_t deviceId);
```

### Parameter

- [In] *context* : Context
- [In] *deviceId* : Device ID

### Return Value

If successfully done, BS\_SDK\_SUCCESS will be returned.

If there is an error, the corresponding error code will be returned.

### See Also

[BS2\\_GetLog](#)

[BS2\\_GetFilteredLog](#)

From:

<http://kb.supremainc.com/bs2sdk/> - **BioStar 2 Device SDK**

Permanent link:

[http://kb.supremainc.com/bs2sdk/doku.php?id=en:bs2\\_clearlog](http://kb.supremainc.com/bs2sdk/doku.php?id=en:bs2_clearlog)

Last update: **2018/02/06 11:28**