

| | | |
|-------------------------|-------|---|
| One Device(Legacy) Mode | | 1 |
| | | 1 |
| | | 3 |

One Device(Legacy) Mode

BioStar 2.5.0 Wiegand 가 Wiegand
 , , + , , , Wiegand

BioStar 2.6.0 **'One Device Mode'** 가 . Wiegand 가
 , 가 () Wiegand 가 Wiegand 가

Authentication Mode: Card(unsupported in Suprema reader) + Fingerprint



가 One Device Mode . Wiegand

1. Wiegand , Wiegand
2. **(Master)** **(Default)** .

One Device Mode Wiegand
(Slave) One Device Mode **(Master)**
(Default/Standalone)

3. **(Format Type)** Wiegand Wiegand **(Wiegand Format)**
Wiegand **(Wiegand Card Format)**

CSN Card Format

- Format Type Wiegand
- Wiegand Format 26 bit SIA Standard-H10301

Wiegand Card Format

- Wiegand Format ID#1 26 bit SIA Standard-H10301

4. **(Advanced) Wiegand (Input/Output) (Input) / (In/Out Format)**

Wiegand

- Input/Output Input
- In/Out Format ID#1 26 bit SIA Standard-H10301
- Output Mode Normal Fail Code 0x00

5. “ + ”
5-1.

가 “ + ”

• Auth Mode

| | | | |
|-------|--------|--|--|
| | Always | | |
| + | Always | | |
| + | Always | | |

5-2.
“ + ”

Wiegand 가
가

Real-time Log

Save Filter Pause Clear ...

| Date | Door | Elevator | Device ID | Device | User | Zone | Event | View |
|---------------------|------------|----------|-----------|-----------------------------------------------|------|------|---------------------------------------------------|------|
| 2018/03/28 11:13:48 | 15F office | | 541531003 | BioStation A2 541531003 (192.168... | | | Door locked | |
| 2018/03/28 11:13:45 | 15F office | | 541531003 | BioStation A2 541531003 (192.168... | | | Door unlocked | |
| 2018/03/28 11:13:45 | | | 541531003 | BioStation A2 541531003 (192.168... 2(hailey) | | | 1:1 authentication succeeded (Card + Fingerprint) | |
| 2018/03/28 11:04:04 | 15F office | | 541531003 | BioStation A2 541531003 (192.168... | | | Door locked | |
| 2018/03/28 11:04:01 | 15F office | | 541531003 | BioStation A2 541531003 (192.168... | | | Door unlocked | |
| 2018/03/28 11:04:01 | | | 541531003 | BioStation A2 541531003 (192.168... 2(hailey) | | | 1:1 authentication succeeded (Card + Fingerprint) | |

| Device | Version |
|---------------|-----------------|
| BioStation 2 | V1.6.0 or above |
| BioStation A2 | V1.5.0 or above |
| BioEntry P2 | V1.1.0 or above |
| BioStation L2 | V1.3.0 or above |
| BioLite N2 | V1.0.0 or above |
| BioEntry W2 | V1.2.0 or above |
| FaceStation 2 | V1.1.0 or above |

- * Entry device which firmware version is V2.x is not supported
- * One Devcie Mode does not support CoreStation

From:
<http://kb.supremainc.com/knowledge/> -

Permanent link:
http://kb.supremainc.com/knowledge/doku.php?id=ko:how_to_configure_one_device_legacy_mode

Last update: **2018/07/11 16:05**