

Table of Contents

| | |
|--------------------------------|---|
| SSL API | 1 |
| <i>Callback Function</i> | 1 |

SSL API

As API that configures the SSL communication, there are communication interfaces include LAN, USB, and RS485. To get real-time device connectivity and search results, please register the callback function via the [BS2_SetDeviceEventListener](#) function.

- [BS2_SetDeviceEventListener](#): Sets device search and network connection event listener.
- [BS2_SearchDevices](#): Search for devices in subnet.
- [BS2_SearchDevicesEx](#): Search for devices in a specific IP address band.
- [BS2_GetDevices](#): Gets the managed device information.
- [BS2_ConnectDevice](#): Connects the device using the device identifier.
- [BS2_ConnectDeviceViaIP](#): Connect devices using IP address and Port.
- [BS2_DisconnectDevice](#): Disconnects from the device.
- [BS2_SetKeepAliveTimeout](#): Sets the keep-alive timeout.
- [BS2_SetNotificationListener](#): Sets the Notification listener.
- [BS2_SetServerPort](#): Set the Server Port.

Callback Function

```
typedef void (*OnDeviceFound)(uint32_t deviceId);
typedef void (*OnDeviceAccepted)(BS2_DEVICE_ID deviceId);
typedef void (*OnDeviceConnected)(uint32_t deviceId);
typedef void (*OnDeviceDisconnected)(uint32_t deviceId);
typedef void (*OnAlarmFired)(BS2_DEVICE_ID deviceId, const BS2Event* event);
typedef void (*OnInputDetected)(BS2_DEVICE_ID deviceId, const BS2Event*
event);
typedef void (*OnConfigChanged)(BS2_DEVICE_ID deviceId, uint32_t
configMask);
```

1. *OnDeviceFound*

Callback function that is called when a new BioStar device is found in Subnet.

2. *OnDeviceAccepted*

Callback function that is called when the BioStar device requests a connection to the BioStar application.

3. *OnDeviceConnected*

Callback function that is called when the device and the BioStar application are connected.

4. *OnDeviceDisconnected*

Callback function that is called when the connection between the device and the BioStar application is lost.

5. *OnAlarmFired*

Callback function that is called when an alarm set in the Zone occurs.

6. *OnInputDetected* Callback function that is called when an input signal is generated.

7. *OnConfigChanged* Callback function that is called when the configuration is changed by manipulating the terminal.

From:

<http://kb.supremainc.com/bs2sdk/> - **BioStar 2 Device SDK**

Permanent link:

http://kb.supremainc.com/bs2sdk/doku.php?id=en:ssl_api&rev=1521529334

Last update: **2018/03/20 16:02**