

- Zone Control API** 1
- 1
- 1
- 2
- / 2
- 2
- 3
- Ethernet 3
- 4
- BS2ZoneStatus 4
- BS2ApbMember 4
- BS2TimedApbMember 5
- BS2FireSensor 5
- BS2AntiPassbackZone 5
- BS2TimedAntiPassbackZone 7
- BS2FireAlarmZone 8
- BS2ScheduledLockUnlockZone 9
- BS2IntrusionAlarmZone 10
- BS2IntrusionAlarmZoneBlob 12
- BS2DeviceZoneEntranceLimitMaster 12
- BS2DeviceZoneEntranceLimitMember 14
- BS2DeviceZoneFireAlarmMaster 14
- BS2DeviceZoneFireAlarmMember 15
- BS2DeviceZoneFireAlarmMemberInfo 16
- BS2DeviceZoneFireSensor 16
- BS2DeviceZone 17
- BS2DeviceZoneAGEntranceLimit 17

Zone Control API

, BioStart

4

가

가

(,)

- [BS2_GetAntiPassbackZone:](#)
- [BS2_GetAllAntiPassbackZone:](#)
- [BS2_GetAntiPassbackZoneStatus:](#)
- [BS2_GetAllAntiPassbackZoneStatus:](#)
- [BS2_SetAntiPassbackZone:](#)
- [BS2_SetAntiPassbackZoneAlarm:](#)
- [BS2_RemoveAntiPassbackZone:](#)
- [BS2_RemoveAllAntiPassbackZone:](#)
- [BS2_ClearAntiPassbackZoneStatus:](#)
- [BS2_ClearAllAntiPassbackZoneStatus:](#)

가

가

가

가

가

가

(,)

- [BS2_GetTimedAntiPassbackZone:](#)
- [BS2_GetAllTimedAntiPassbackZone:](#)
- [BS2_GetTimedAntiPassbackZoneStatus:](#)
- [BS2_GetAllTimedAntiPassbackZoneStatus:](#)
- [BS2_SetTimedAntiPassbackZone:](#)
- [BS2_SetTimedAntiPassbackZoneAlarm:](#)
- [BS2_RemoveTimedAntiPassbackZone:](#)
- [BS2_RemoveAllTimedAntiPassbackZone:](#)
- [BS2_ClearTimedAntiPassbackZoneStatus:](#)
- [BS2_ClearAllTimedAntiPassbackZoneStatus:](#)

가

가

가

가

가 BioStar

BioStar

- [BS2_GetFireAlarmZone:](#)
- [BS2_GetAllFireAlarmZone:](#)
- [BS2_GetFireAlarmZoneStatus:](#)
- [BS2_GetAllFireAlarmZoneStatus:](#)
- [BS2_SetFireAlarmZone:](#)
- [BS2_SetFireAlarmZoneAlarm:](#)
- [BS2_RemoveFireAlarmZone:](#)
- [BS2_RemoveAllFireAlarmZone:](#)

가
가

가
가

/

/

- [BS2_GetScheduledLockUnlockZone:](#)
- [BS2_GetAllScheduledLockUnlockZone:](#)
- [BS2_GetScheduledLockUnlockZoneStatus:](#)
- [BS2_GetAllScheduledLockUnlockZoneStatus:](#)
- [BS2_SetScheduledLockUnlockZone:](#)
- [BS2_SetScheduledLockUnlockZoneAlarm:](#)
- [BS2_RemoveScheduledLockUnlockZone:](#)
- [BS2_RemoveAllScheduledLockUnlockZone:](#)

/
/

가
가

가
가

가 BioStar

가

BioStar

- [BS2_GetIntrusionAlarmZone:](#)
- [BS2_GetIntrusionAlarmZoneStatus:](#)
- [BS2_GetAllIntrusionAlarmZoneStatus:](#)
- [BS2_SetIntrusionAlarmZone:](#)
- [BS2_SetIntrusionAlarmZoneAlarm:](#)
- [BS2_RemoveIntrusionAlarmZone:](#)
- [BS2_RemoveAllIntrusionAlarmZone:](#)
- [BS2_SetIntrusionAlarmZoneArm:](#)

가

가
가

/

- [BS2_GetInterlockZone:](#) 가 .
- [BS2_GetInterlockZoneStatus:](#) 가 .
- [BS2_GetAllInterlockZoneStatus:](#) 가 .
- [BS2_SetInterlockZone:](#) .
- [BS2_SetInterlockZoneAlarm:](#) .
- [BS2_RemoveInterlockZone:](#) .
- [BS2_RemoveAllInterlockZone:](#) .

Ethernet

Zone Master BioStar V2.x 가 Zone 가 (Master ↔ Member)
 Ethernet TCP 1.x Entrance Limit, Fire Alarm Zone

- [BS2_GetDeviceZone:](#) Ethernet 가 .
- [BS2_GetAllDeviceZone:](#) Ethernet 가 .
- [BS2_SetDeviceZone:](#) Ethernet .
- [BS2_RemoveDeviceZone:](#) Ethernet .
- [BS2_RemoveAllDeviceZone:](#) Ethernet .
- [BS2_SetDeviceZoneAlarm:](#) Ethernet .
- [BS2_ClearDeviceZoneAccessRecord:](#) Ethernet .
- [BS2_ClearAllDeviceZoneAccessRecord:](#) Ethernet .
- [BS2_GetAccessGroupEntranceLimit:](#) 가 .
- [BS2_GetAllAccessGroupEntranceLimit:](#) 가 .
- [BS2_SetAccessGroupEntranceLimit:](#) .
- [BS2_RemoveAccessGroupEntranceLimit:](#) .
- [BS2_RemoveAllAccessGroupEntranceLimit:](#) .
- [BS2_GetDeviceZoneAGEntranceLimit:](#) Ethernet Access Group 가
- [BS2_GetAllDeviceZoneAGEntranceLimit:](#) Ethernet Access Group 가
- [BS2_SetDeviceZoneAGEntranceLimit:](#) Ethernet Access Group .
- [BS2_RemoveDeviceZoneAGEntranceLimit:](#) Ethernet Access Group .
- [BS2_RemoveAllDeviceZoneAGEntranceLimit:](#) Ethernet Access Group .

BS2ZoneStatus

```
typedef struct {  
    uint32_t id;  
    uint8_t status;  
    uint8_t disabled;  
    uint8_t reserved[6];  
} BS2ZoneStatus;
```

1. *id*

2. *status*

0	
1	
2	scheduled lock
4	scheduled unlock

3. *disabled*

flag

4. *reserved*

BS2ApbMember

```
typedef struct {  
    uint32_t deviceID;  
    uint8_t type;  
    uint8_t reserved[3];  
} BS2ApbMember;
```

1. *deviceID*

2. *type*

APB reader

-1	

0	
1	

3. reserved

BS2TimedApbMember

```
typedef struct {
    uint32_t deviceID;
    uint8_t reserved[4];
} BS2TimedApbMember;
```

1. deviceID

2. reserved

BS2FireSensor

```
typedef struct {
    uint32_t deviceID;
    uint8_t port;
    uint8_t switchType;
    uint8_t duration;
} BS2FireSensor ;
```

1. deviceID

2. port

3. switchType

0	
1	

4. duration

millisecond

BS2AntiPassbackZone

```
typedef struct {
```

```

uint32_t zoneID;
char name[BS2_MAX_ZONE_NAME_LEN];
uint8_t type;
uint8_t numReaders;
uint8_t numBypassGroups;
uint8_t disabled;
uint8_t alarmed;
uint8_t reserved[3];
uint32_t resetDuration;
BS2Action alarm[BS2_MAX_APB_ALARM_ACTION];
BS2ApbMember readers[BS2_MAX_READERS_PER_APB_ZONE];
uint8_t reserved2[512];
uint32_t bypassGroupIDs[BS2_MAX_BYPASS_GROUPS_PER_APB_ZONE];
} BS2AntiPassbackZone;

```

1. zoneID

1 가 .

가 .

2. name

BioStar .

3. type

0	Hard APB(가)
1	Soft APB()

4. numReaders

APB reader .

5. numBypassGroups

APB .

6. disabled

flag .

7. alarmed

8. reserved

9. resetDuration

가 APB			
0			BioStar
10. alarm			
가 APB	5		
11. readers			
		64	
12. reserved2			
13. bypassGroupIDs			
APB		16	

BS2TimedAntiPassbackZone

```
typedef struct {
    uint32_t zoneID;
    char name[BS2_MAX_ZONE_NAME_LEN];
    uint8_t type;
    uint8_t numReaders;
    uint8_t numBypassGroups;
    uint8_t disabled;
    uint8_t alarmed;
    uint8_t reserved[3];
    uint32_t resetDuration;
    BS2Action alarm[BS2_MAX_TIMED_APB_ALARM_ACTION];
    BS2TimedApbMember readers[BS2_MAX_READERS_PER_TIMED_APB_ZONE];
    uint8_t reserved2[320];
    uint32_t bypassGroupIDs[BS2_MAX_BYPASS_GROUPS_PER_TIMED_APB_ZONE];
} BS2TimedAntiPassbackZone;
```

1. zoneID

1 가

2. name

BioStar

3. type

0	Hard APB(가)
1	Soft APB()

4. numReaders

reader

5. *numBypassGroups*6. *disabled*

flag

7. *alarmed*8. *reserved*9. *resetDuration*

가

0

BioStar

10. *alarm*

가

5

11. *readers*

64

12. *reserved2*13. *bypassGroupIDs*

16

BS2FireAlarmZone

```
typedef struct {
    uint32_t zoneID;
    char name[BS2_MAX_ZONE_NAME_LEN];
    uint8_t numSensors;
    uint8_t numDoors;
    uint8_t disabled;
    uint8_t alarmed;
    uint8_t reserved[8];
    BS2FireSensor sensor[BS2_MAX_FIRE_SENSORS_PER_FIRE_ALARM_ZONE];
    BS2Action alarm[BS2_MAX_FIRE_ALARM_ACTION];
    uint8_t reserved2[32];
    uint32_t doorIDs[BS2_MAX_DOORS_PER_FIRE_ALARM_ZONE];
} BS2FireAlarmZone;
```

1. *zoneID*

1

가

2. *name*

BioStar

3. *numSensors*

4. *numDoors*

5. *alarmed*

6. *disabled*
flag

7. *reserved*

8. *sensor* 8

9. *alarm* 5

10. *reserved2*

11. *doorIDs* 32

BS2ScheduledLockUnlockZone

```
typedef struct {
    uint32_t zoneID;
    char name[BS2_MAX_ZONE_NAME_LEN];
    uint32_t lockScheduleID;
    uint32_t unlockScheduleID;
    uint8_t numDoors;
    uint8_t numBypassGroups;
    uint8_t numUnlockGroups;
    uint8_t bidirectionalLock;
    uint8_t disabled;
    uint8_t alarmed;
    uint8_t reserved[6];
    BS2Action alarm[BS2_MAX_SCHEDULED_LOCK_UNLOCK_ALARM_ACTION];
    uint8_t reserved2[32];
    uint32_t doorIDs[BS2_MAX_DOORS_IN_SCHEDULED_LOCK_UNLOCK_ZONE];
    uint32_t
bypassGroupIDs[BS2_MAX_BYPASS_GROUPS_IN_SCHEDULED_LOCK_UNLOCK_ZONE];
    uint32_t
unlockGroupIDs[BS2_MAX_UNLOCK_GROUPS_IN_SCHEDULED_LOCK_UNLOCK_ZONE];
} BS2ScheduledLockUnlockZone;
```

1. <i>zoneID</i>	1	가	.
2. <i>name</i>			.
BioStar			.
3. <i>lockScheduleID</i>			.
4. <i>unlockScheduleID</i>			.
5. <i>numDoors</i>			.
6. <i>numBypassGroups</i>			.
7. <i>numUnlockGroups</i>		가	.
8. <i>bidirectionalLock</i>			.
9. <i>disabled</i>	flag	.	.
10. <i>alarmed</i>			.
11. <i>reserved</i>			.
12. <i>alarm</i>		5	.
13. <i>reserved2</i>			.
14. <i>doorIDs</i>		32	.
15. <i>bypassGroupIDs</i>			16
16. <i>unlockGroupIDs</i>		가	.
16			.

BS2IntrusionAlarmZone

```
typedef struct {
```

```
uint32_t zoneID;  
char name[BS2_MAX_ZONE_NAME_LEN];  
uint8_t armDelay;  
uint8_t alarmDelay;  
uint8_t disabled;  
uint8_t reserved[1];  
uint8_t numReaders;  
uint8_t numInputs;  
uint8_t numOutputs;  
uint8_t numCards;  
uint8_t numDoors;  
uint8_t numGroups;  
uint8_t reserved2[10];  
} BS2IntrusionAlarmZone;
```

1. *zoneID*

1 가

2. *name*

BioStar

3. *armDelay*

4. *alarmDelay*

5. *disabled*

flag

6. *reserved[1]*

7. *numReaders*

8. *numInputs*

9. *numOutputs*

10. *numCards*

11. *numDoors*

12. *numGroups*

13. *reserved*

BS2IntrusionAlarmZoneBlob

```
typedef struct {
    BS2IntrusionAlarmZone IntrusionAlarmZone;
    BS2AlarmZoneMember* memberObjs;
    BS2AlarmZoneInput* inputObjs;
    BS2AlarmZoneOutput* outputObjs;
    BS2CSNCard* cardObjs;
    BS2_D00R_ID* doorIDs;
    BS2_ACCESS_GROUP_ID* groupIDs;
} BS2IntrusionAlarmZoneBlob;
```

1. *IntrusionAlarmZone*

2. *memberObjs*

IntrusionAlarmZone.numReaders

3. *inputObjs*

IntrusionAlarmZone.numInputs

4. *outputObjs*

IntrusionAlarmZone.numOutputs

5. *cardObjs*

IntrusionAlarmZone.numCards

[Smartcard API](#)

6. *doorIDs*

IntrusionAlarmZone.numDoors

7. *groupIDs*

IntrusionAlarmZone.numGroups

BS2DeviceZoneEntranceLimitMaster

```
typedef struct {
    char name[BS2_MAX_ZONE_NAME_LEN];
    uint8_t type;
    uint8_t reserved1[3];
    uint32_t entryLimitInterval_s;
    uint8_t numEntranceLimit;
    uint8_t numReaders;
    uint8_t numAlarm;
    uint8_t numBypassGroups;
```

```

uint8_t maxEntry[BS2_MAX_ENTRANCE_LIMIT_PER_ZONE];
uint32_t periodStart_s[BS2_MAX_ENTRANCE_LIMIT_PER_ZONE];
uint32_t periodEnd_s[BS2_MAX_ENTRANCE_LIMIT_PER_ZONE];
BS2DeviceZoneEntranceLimitMemberInfo
readers[BS2_MAX_READERS_PER_DEVICE_ZONE_ENTRANCE_LIMIT];
BS2Action alarm[BS2_MAX_DEVICE_ZONE_ENTRANCE_LIMIT_ALARM_ACTION];
BS2_ACCESS_GROUP_ID
bypassGroupIDs[BS2_MAX_BYPASS_GROUPS_PER_DEVICE_ZONE_ENTRANCE_LIMIT];
uint8_t reserved3[8 * 4];
} BS2DeviceZoneEntranceLimitMaster;
    
```

1. name

BioStar

2. type

1	Soft EntranceLimit()	가
2	Hard EntranceLimit()	

3. reserved1[3]

4. entryLimitInterval_s

5. numEntranceLimit

6. numReaders
reader

7. numAlarm

8. numBypassGroups

9. maxEntry

10. periodStart_s
가 ()

11. periodEnd_s
가 ()

12. readers

13. *alarm*

5

14. *bypassGroupIDs*

16

15. *reserved3*

BS2DeviceZoneEntranceLimitMember

```
typedef struct {
    uint16_t masterPort;
    BS2_DEVICE_ZONE_ENTRANCE_LIMIT_DISCONNECTED_ACTION_TYPE
actionInDisconnect;
    uint8_t reserved1[1];
    BS2_IPV4_ADDR masterIP;
} BS2DeviceZoneEntranceLimitMember;
```

1. *masterPort*

master port

2. *actionInDisconnect*

Disconnect

1	Soft EntranceLimit Disconnected action(가)
2	Hard EntranceLimit Disconnected action()

3. *reserved1[3]*

4. *masterIP*

master IP

BS2DeviceZoneFireAlarmMaster

```
typedef struct {
    char name[BS2_MAX_ZONE_NAME_LEN];
    uint8_t numReaders;
    uint8_t numAlarm;
    uint8_t reserved1[2];
    BS2DeviceZoneFireAlarmMemberInfo
readers[BS2_MAX_READERS_PER_DEVICE_ZONE_FIRE_ALARM];
    BS2Action alarm[BS2_MAX_DEVICE_ZONE_FIRE_ALARM_ALARM_ACTION];
```

```
uint8_t reserved2[8 * 40];  
} BS2DeviceZoneFireAlarmMaster;
```

1. *name*

BioStar

2. *numReaders*

3. *reserved1*

4. *readers*

5. *alarm*

5

6. *reserved2*

BS2DeviceZoneFireAlarmMember

```
typedef struct {  
    BS2_PORT masterPort;  
    uint8_t reserved1[2];  
    BS2_IPV4_ADDR masterIP;  
    uint8_t numSensors;  
    uint8_t numDoors;  
    uint8_t reserved2[2];  
    BS2DeviceZoneFireSensor  
sensor[BS2_MAX_FIRE_SENSORS_PER_DEVICE_ZONE_FIRE_ALARM_MEMBER];  
    union {  
        BS2_D00R_ID  
doorIDs[BS2_MAX_DOORS_PER_DEVICE_ZONE_FIRE_ALARM_MEMBER];  
        BS2_LIFT_ID  
liftIDs[BS2_MAX_DOORS_PER_DEVICE_ZONE_FIRE_ALARM_MEMBER];  
    };  
} BS2DeviceZoneFireAlarmMember;
```

1. *masterPort*

master port

2. *reserved1*

3. *masterIP*

master IP

4. *numSensors*

5. *numDoors*

6. *reserved2*

7. *sensor*

8

8. *doorIDs*

8

9. *liftIDs*

Lift

8

BS2DeviceZoneFireAlarmMemberInfo

```
typedef struct {
    uint32_t readerID;
} BS2DeviceZoneFireAlarmMemberInfo;
```

1. *readerID*

BS2DeviceZoneFireSensor

```
typedef struct {
    uint32_t deviceID;
    uint8_t port;
    uint8_t switchType;
    uint16_t duration;
} BS2DeviceZoneFireSensor;
```

1. *deviceID*

2. *port*

3. *switchType*

0	
1	

4. *duration*

millisecond

BS2DeviceZone

```
typedef struct {
    uint32_t zoneID;
    uint8_t zoneType;
    uint8_t nodeType;
    uint8_t enable;
    uint8_t reserved[1];
    union {
        BS2DeviceZoneEntranceLimitMaster entranceLimitMaster;
        BS2DeviceZoneEntranceLimitMember entranceLimitMember;
        BS2DeviceZoneFireAlarmMaster fireAlarmMaster;
        BS2DeviceZoneFireAlarmMember fireAlarmMember;
    };
} BS2DeviceZone;
```

1. *zoneID*

1 가 .

2. *zoneType*

.

3. *nodeType*

.

4. *enable*

flag .

5. *reserved[1]*

.

BS2DeviceZoneAGEntranceLimit

```
typedef struct {
    uint32_t zoneID;
    uint16_t numAGEntranceLimit;
    uint16_t reserved1;
    uint32_t periodStart_s[BS2_MAX_ENTRANCE_LIMIT_PER_ZONE];
    uint32_t periodEnd_s[BS2_MAX_ENTRANCE_LIMIT_PER_ZONE];
    uint16_t numEntry[BS2_MAX_ENTRANCE_LIMIT_PER_ZONE];
    uint16_t
maxEntry[BS2_MAX_ENTRANCE_LIMIT_PER_ZONE][BS2_MAX_ACCESS_GROUP_ENTRANCE_LIMI
T_PER_ENTRANCE_LIMIT];
    uint32_t
accessGroupID[BS2_MAX_ENTRANCE_LIMIT_PER_ZONE][BS2_MAX_ACCESS_GROUP_ENTRANCE
_LIMIT_PER_ENTRANCE_LIMIT];
} BS2DeviceZoneAGEntranceLimit;
```

1. *zoneID*

1 가 .

2. numAGEntranceLimit

3. reserved1

4. periodStart_s
가 .

5. periodEnd_s
가 .

6. numEntry

7. maxEntry

8. accessGroupID

16

From:

<https://kb.supremainc.com/bs2sdk/> - **BioStar 2 Device SDK**

Permanent link:

https://kb.supremainc.com/bs2sdk/doku.php?id=ko:zone_control_api&rev=1520389395

Last update: **2018/03/07 11:23**