

**Smartcard API** ..... 1

..... 1

BS2CSNCard ..... 1

BS2SmartCardHeader ..... 2

BS2SmartCardCredentials ..... 3

BS2AccessOnCardData ..... 3

BS2SmartCardData ..... 3

BS2Card ..... 4

# Smartcard API

## API

- [BS2\\_ScanCard](#):
- [BS2\\_WriteCard](#): SmartCard
- [BS2\\_EraseCard](#): SmartCard

## BS2CSNCard

```
typedef struct {
    uint8_t type;
    uint8_t size;
    uint8_t data[BS2_CARD_DATA_SIZE];
} BS2CSNCard;
```

### 1. type

0x00		
0x01	CSN	
0x02	Secure	
0x03	Access	
0x0A	Wiegand	BS2WiegandConfig.format ( BS2WiegandConfig.CSNIndex BS2WiegandConfig.CardMask & 0
0x1A	Wiegand	BS2WiegandMultiConfig.formats[0]
0x2A	Wiegand	BS2WiegandMultiConfig.formats[1]
0x3A	Wiegand	BS2WiegandMultiConfig.formats[2]
0x4A	Wiegand	BS2WiegandMultiConfig.formats[3]
0x5A	Wiegand	BS2WiegandMultiConfig.formats[4]
0x6A	Wiegand	BS2WiegandMultiConfig.formats[5]
0x7A	Wiegand	BS2WiegandMultiConfig.formats[6]
0x8A	Wiegand	BS2WiegandMultiConfig.formats[7]
0x9A	Wiegand	BS2WiegandMultiConfig.formats[8]
0xAA	Wiegand	BS2WiegandMultiConfig.formats[9]
0xBA	Wiegand	BS2WiegandMultiConfig.formats[10]
0xCA	Wiegand	BS2WiegandMultiConfig.formats[11]
0xDA	Wiegand	BS2WiegandMultiConfig.formats[12]
0xEA	Wiegand	BS2WiegandMultiConfig.formats[13]
0xFA	Wiegand	BS2WiegandMultiConfig.formats[14]

### 2. size

### 3. data

## BS2SmartCardHeader

```

typedef struct {
    uint16_t hdrCRC;
    uint16_t cardCRC;
    BS2_CARD_TYPE cardType;
    uint8_t numOfTemplate;
    uint16_t templateSize;
    uint16_t issueCount;
    uint8_t duressMask;
    uint8_t reserved[5];
} BS2SmartCardHeader;

```

1. *hdrCRC*  
card header

2. *cardCRC*  
card data

3. *cardType*

0	
1	CSN
2	Secure
3	Access
4	Wiegand

4. *numOfTemplate*

5. *templateSize*

BioStar 2 가 300 가 384 가 300

6. *issueCount*

7. *duressMask*

## BS2SmartCardCredentials

```
typedef struct {
    uint8_t pin[BS2_PIN_HASH_SIZE];
    uint8_t templateData[BS2_SMART_CARD_MAX_TEMPLATE_COUNT *
BS2_FINGER_TEMPLATE_SIZE];
} BS2SmartCardCredentials;
```

### 1. *pin*

pin code

### 2. *templateData*

4

## BS2AccessOnCardData

```
typedef struct {
    uint16_t accessGroupID[BS2_SMART_CARD_MAX_ACCESS_GROUP_COUNT];
    BS2_DATETIME startTime;
    BS2_DATETIME endTime;
} BS2AccessOnCardData;
```

### 1. *accessGroupID*

### 2. *startTime*

가 , 0

### 3. *endTime*

가 , 0

## BS2SmartCardData

```
typedef struct {
    BS2SmartCardHeader header;
    uint8_t cardID[BS2_CARD_DATA_SIZE];
    BS2SmartCardCredentials credentials;
    BS2AccessOnCardData accessOnData;
} BS2SmartCardData;
```

### 1. *header*

SmartCard

### 2. *cardID*

### 3. *credentials*

pin code

### 3. *accessOnData*

AOC

가

## BS2Card

```
typedef struct {  
    uint8_t isSmartCard;  
    union {  
        BS2CSNCard card;  
        BS2SmartCardData smartCard;  
    };  
}BS2Card;
```

#### 1. *isSmartCard*

SmartCard

flag

#### 2. *card*

#### 3. *smartCard*

SmartCard

From:

<https://kb.supremainc.com/bs2sdk/> - **BioStar 2 Device SDK**

Permanent link:

[https://kb.supremainc.com/bs2sdk/doku.php?id=ko:smartcard\\_api&rev=1519171509](https://kb.supremainc.com/bs2sdk/doku.php?id=ko:smartcard_api&rev=1519171509)

Last update: **2018/02/21 09:05**