

- Smartcard API** 1
- 1
- BS2CSNCard 1
- BS2SmartCardHeader 2
- BS2SmartCardCredentials 4
- BS2AccessOnCardData 4
- BS2SmartCardData 4
- BS2Card 5

Smartcard API

API

- [BS2_ScanCard](#):
- [BS2_WriteCard](#): SmartCard
- [BS2_EraseCard](#): SmartCard

BS2CSNCard

```
typedef struct {
    uint8_t type;
    uint8_t size;
    uint8_t data[BS2_CARD_DATA_SIZE];
} BS2CSNCard;
```

1. type

Access

가

0x00		
0x01	CSN	
0x02	Secure	
0x03	Access	
0x0A	Wiegand	BS2WiegandConfig.format (BS2WiegandConfig.CSNIndex BS2WiegandConfig.CardMask가 0
0x0B	Config	
0x1A	Wiegand	BS2WiegandMultiConfig.formats[0]
0x2A	Wiegand	BS2WiegandMultiConfig.formats[1]
0x3A	Wiegand	BS2WiegandMultiConfig.formats[2]
0x4A	Wiegand	BS2WiegandMultiConfig.formats[3]
0x5A	Wiegand	BS2WiegandMultiConfig.formats[4]
0x6A	Wiegand	BS2WiegandMultiConfig.formats[5]
0x7A	Wiegand	BS2WiegandMultiConfig.formats[6]
0x8A	Wiegand	BS2WiegandMultiConfig.formats[7]
0x9A	Wiegand	BS2WiegandMultiConfig.formats[8]
0xAA	Wiegand	BS2WiegandMultiConfig.formats[9]
0xBA	Wiegand	BS2WiegandMultiConfig.formats[10]
0xCA	Wiegand	BS2WiegandMultiConfig.formats[11]
0xDA	Wiegand	BS2WiegandMultiConfig.formats[12]
0xEA	Wiegand	BS2WiegandMultiConfig.formats[13]

6. issueCount

7. duressMask

8. cardAuthMode

FaceStation F2

FaceStation F2 **cardAuthModeEx**

2	
3	
4	PIN
5	PIN
6	, , PIN
254	
255	()

9. useAlphanumericID

Alphanumeric ID flag

10. cardAuthModeEx

FaceStation F2 **cardAuthMode**

[+ V2.7.1] FaceStation F2

	1	2	3
21			
22			
23			
24		PIN	
25			
26		PIN	
27		PIN	
28		PIN	
29			
30			PIN
31			
32			PIN
33			PIN
34			PIN
35			PIN
254			
255			

11. numOfFaceTemplate

template 가 (:384, :552)
BS2SmartCardCredentials templateData

12. reserved

BS2SmartCardCredentials

```
typedef struct {
    uint8_t pin[BS2_PIN_HASH_SIZE];
    uint8_t templateData[BS2_SMART_CARD_MAX_TEMPLATE_COUNT *
BS2_FINGER_TEMPLATE_SIZE];
} BS2SmartCardCredentials;
```

1. pin

pin code

2. templateData

4

BS2AccessOnCardData

```
typedef struct {
    uint16_t accessGroupID[BS2_SMART_CARD_MAX_ACCESS_GROUP_COUNT];
    BS2_DATETIME startTime;
    BS2_DATETIME endTime;
} BS2AccessOnCardData;
```

1. accessGroupID

2. startTime

가 , 0

3. endTime

가 , 0

BS2SmartCardData

```
typedef struct {
    BS2SmartCardHeader header;
    uint8_t cardID[BS2_CARD_DATA_SIZE];
    BS2SmartCardCredentials credentials;
    BS2AccessOnCardData accessOnData;
} BS2SmartCardData;
```

1. header

SmartCard

2. cardID

Access on Card	32 byte	Card ID	
Secure Credential card	24 byte	Card ID	
Secure Credential Card(SCC) Stamp(4 byte)	32 byte	Card ID(24 bytes), issueCount(4 byte)	Time
, BS2UserBlob	cardObjs array가	SC Card	, SC Card cardObjs

3. credentials

pin code

4. accessOnData

AOC 가

BS2Card

```
typedef struct {
    uint8_t isSmartCard;
    union {
        BS2CSNCard card;
        BS2SmartCardData smartCard;
    };
}BS2Card;
```

1. isSmartCard

SmartCard flag

2. card

3. smartCard

SmartCard

From:
<http://kb.supremainc.com/bs2sdk/> - **BioStar 2 Device SDK**

Permanent link:
http://kb.supremainc.com/bs2sdk/doku.php?id=ko:smartcard_api&rev=1597983084

Last update: **2020/08/21 13:11**