

# Table of Contents

<b>BS2_PartialUpdateUserSmall</b> .....	1
Declaration .....	1
파라미터 .....	1
반환값 .....	2
함께 보기 .....	2
샘플코드 .....	2

 **This page is not fully translated, yet. Please help completing the translation.**  
(remove this paragraph once the translation is finished)

User Management API > [BS2\\_PartialUpdateUserSmall](#)

## BS2\_PartialUpdateUserSmall

[+ 2.8.3] Updates partial information of an already registered user. The user you want to renew must be a registered user.

You can optionally specify the partial information you want to update using the mask.

If you want to delete partial information, you can delete it in combination with [BS2User](#) infoMask.

### Declaration

```
#include "BS_API.h"

int BS2_PartialUpdateUserSmall(void* context, uint32_t deviceId,
BS2_USER_MASK mask, BS2UserSmallBlob* userBlob, uint32_t userCount);
```

[See BS2UserSmallBlob Structure](#)

### 파라미터

- [In] *context* : Context
- [In] *deviceId* : 장치 식별자
- [In] *mask* : 갱신하고자 하는 사용자 부분에 대한 mask

값	설명
0x0002	사용자설정(개인인증모드,유효기간)
0x0004	사용자명
0x0008	이미지
0x0010	PIN
0x0020	카드
0x0040	지문
0x0080	얼굴
0x0100	출입그룹
0x0200	작업코드
0x0400	개인메시지
0x0800	얼굴 (FSF2, BS3)
0x1000	사용자설정 (FSF2, BS3)

- [In] *userBlob* : 갱신하고자 하는 사용자 부분 정보

- [In] *userCount* : 사용자 개수

## 반환값

성공적으로 수행될 경우 `BS_SDK_SUCCESS`를 반환하고,  
`BS2_EVENT_USER_UPDATE_PARTIAL_SUCCESS` 이벤트가 발생합니다.  
실패했을 경우 상응하는 에러 코드를 반환하고, 장치 발생 오류라면  
`BS2_EVENT_USER_UPDATE_PARTIAL_FAIL` 이벤트가 발생합니다.

## 함께 보기

[BS2\\_PartialUpdateUser](#)

[BS2\\_PartialUpdateUserEx](#)

[BS2\\_PartialUpdateUserSmall](#)

[BS2\\_PartialUpdateUserSmallEx](#)

[BS2\\_PartialUpdateUserFaceEx](#)

## 샘플코드

[BS2\\_PartialUpdateUserFaceEx](#)의 샘플코드 참조

From:  
<https://kb.supremainc.com/kbtest/> - **BioStar Device SDK**

Permanent link:  
[https://kb.supremainc.com/kbtest/doku.php?id=en:bs2\\_partialupdateusersmall&rev=1662514030](https://kb.supremainc.com/kbtest/doku.php?id=en:bs2_partialupdateusersmall&rev=1662514030)

Last update: **2022/09/07 10:27**