

Zone Control API	1
.....	1
.....	1
.....	2
/	2
.....	2
.....	3
Ethernet	3
Lift /	4
.....	4
OnCheckGlobalAPBViolation	4
OnCheckGlobalAPBViolationByDoorOpen	4
OnUpdateGlobalAPBViolationByDoorOpen	5
.....	6
BS2ZoneStatus	6
BS2ApbMember	6
BS2TimedApbMember	7
BS2FireSensor	7
BS2AntiPassbackZone	7
BS2TimedAntiPassbackZone	9
BS2FireAlarmZone	10
BS2ScheduledLockUnlockZone	11
BS2IntrusionAlarmZone	12
BS2IntrusionAlarmZoneBlob	13
BS2InterlockZone	14
BS2InterlockZoneBlob	15
BS2DeviceZoneEntranceLimitMaster	15
BS2DeviceZoneEntranceLimitMember	17
BS2DeviceZoneFireAlarmMaster	17
BS2DeviceZoneFireAlarmMember	18
BS2DeviceZoneFireAlarmMemberInfo	19
BS2DeviceZoneFireSensor	19
BS2DeviceZone	20
BS2DeviceZoneAGEntranceLimit	20
BS2LiftFloors	21
BS2LiftLockUnlockZone	22

Zone Control API

가

- 가 (,)
- [BS2_GetAntiPassbackZone:](#) 가
 - [BS2_GetAllAntiPassbackZone:](#) 가
 - [BS2_GetAntiPassbackZoneStatus:](#) 가
 - [BS2_GetAllAntiPassbackZoneStatus:](#) 가
 - [BS2_SetAntiPassbackZone:](#)
 - [BS2_SetAntiPassbackZoneAlarm:](#)
 - [BS2_RemoveAntiPassbackZone:](#)
 - [BS2_RemoveAllAntiPassbackZone:](#)
 - [BS2_ClearAntiPassbackZoneStatus:](#)
 - [BS2_ClearAllAntiPassbackZoneStatus:](#)
 - [BS2_SetCheckGlobalAPBViolationHandler:](#) 가
 - [BS2_CheckGlobalAPBViolation:](#)
 - [BS2_SetGlobalAPBViolationByDoorOpenHandler:](#) [+ 2.7.0]
가
 - [BS2_CheckGlobalAPBViolationByDoorOpen:](#) [+ 2.7.0]
-

- 가 (, ,)
- [BS2_GetTimedAntiPassbackZone:](#) 가
 - [BS2_GetAllTimedAntiPassbackZone:](#) 가
 - [BS2_GetTimedAntiPassbackZoneStatus:](#) 가
 - [BS2_GetAllTimedAntiPassbackZoneStatus:](#) 가
 - [BS2_SetTimedAntiPassbackZone:](#)
 - [BS2_SetTimedAntiPassbackZoneAlarm:](#)
 - [BS2_RemoveTimedAntiPassbackZone:](#)
 - [BS2_RemoveAllTimedAntiPassbackZone:](#)
-

- [BS2_ClearTimedAntiPassbackZoneStatus:](#)
- [BS2_ClearAllTimedAntiPassbackZoneStatus:](#)

가 BioStar	BioStar				
• BS2_GetFireAlarmZone:		가	.		
• BS2_GetAllFireAlarmZone:		가	.		
• BS2_GetFireAlarmZoneStatus:				가	.
• BS2_GetAllFireAlarmZoneStatus:				가	.
• BS2_SetFireAlarmZone:		.			
• BS2_SetFireAlarmZoneAlarm:				.	
• BS2_RemoveFireAlarmZone:			.		
• BS2_RemoveAllFireAlarmZone:			.		

/					
		/	.		
		,			
• BS2_GetScheduledLockUnlockZone:		/		가	.
• BS2_GetAllScheduledLockUnlockZone:		/		가	.
• BS2_GetScheduledLockUnlockZoneStatus:			/		가
• BS2_GetAllScheduledLockUnlockZoneStatus:			/		가
• BS2_SetScheduledLockUnlockZone:		/	.		
• BS2_SetScheduledLockUnlockZoneAlarm:		/		.	
• BS2_RemoveScheduledLockUnlockZone:			/	.	
• BS2_RemoveAllScheduledLockUnlockZone:			/	.	

	가				
가 BioStar	BioStar				
• BS2_GetIntrusionAlarmZone:		가	.		
• BS2_GetIntrusionAlarmZoneStatus:				가	.
• BS2_GetAllIntrusionAlarmZoneStatus:				가	.
• BS2_SetIntrusionAlarmZone:		.			
• BS2_SetIntrusionAlarmZoneAlarm:			.		

- [BS2_RemoveIntrusionAlarmZone:](#) .
- [BS2_RemoveAllIntrusionAlarmZone:](#) .
- [BS2_SetIntrusionAlarmZoneArm:](#) / .

[CoreStation]

CoreStation

- [BS2_GetInterlockZone:](#) 가 .
- [BS2_GetInterlockZoneStatus:](#) 가 .
- [BS2_GetAllInterlockZoneStatus:](#) 가 .
- [BS2_SetInterlockZone:](#) .
- [BS2_SetInterlockZoneAlarm:](#) .
- [BS2_RemoveInterlockZone:](#) .
- [BS2_RemoveAllInterlockZone:](#) .

Ethernet

Zone Master BioStar V2.x 가 가 (Master ↔ Member)
Ethernet TCP Zone 1.x Entrance Limit, Fire Alarm Zone
. A2(FW 1.4.0), BS2(FW 1.5.0) and P2(FW 1.0.0)

- [BS2_GetDeviceZone:](#) Ethernet 가 .
- [BS2_GetAllDeviceZone:](#) Ethernet 가 .
- [BS2_SetDeviceZone:](#) Ethernet .
- [BS2_RemoveDeviceZone:](#) Ethernet .
- [BS2_RemoveAllDeviceZone:](#) Ethernet .
- [BS2_SetDeviceZoneAlarm:](#) Ethernet .
- [BS2_ClearDeviceZoneAccessRecord:](#) Ethernet .
- [BS2_ClearAllDeviceZoneAccessRecord:](#) Ethernet .
- [BS2_GetDeviceZoneAGEntranceLimit:](#) Ethernet Access Group 가
- [BS2_GetAllDeviceZoneAGEntranceLimit:](#) Ethernet Access Group 가
- [BS2_SetDeviceZoneAGEntranceLimit:](#) Ethernet Access Group .
- [BS2_RemoveDeviceZoneAGEntranceLimit:](#) Ethernet Access Group .
- [BS2_RemoveAllDeviceZoneAGEntranceLimit:](#) Ethernet Access Group .

Lift /

[+ 2.7.0] Elevator ,

- [BS2_GetLiftLockUnlockZone](#): Lift / 가 .
- [BS2_GetAllLiftLockUnlockZone](#): Lift / 가 .
- [BS2_GetLiftLockUnlockZoneStatus](#): Lift / 가 .
- [BS2_GetAllLiftLockUnlockZoneStatus](#): Lift / 가 .
- [BS2_SetLiftLockUnlockZone](#): Lift / .
- [BS2_SetLiftLockUnlockZoneAlarm](#): Lift / .
- [BS2_RemoveLiftLockUnlockZone](#): Lift / .
- [BS2_RemoveAllLiftLockUnlockZone](#): Lift / .

OnCheckGlobalAPBViolation

가 .

```
typedef void (*OnCheckGlobalAPBViolation)(uint32_t deviceId, uint16_t seq,
const char* userID_1, const char* userID_2, bool isDualAuth);
```

1. *deviceId* .
2. *seq* .
3. *userID_1* ID .
4. *userID_2* ID .
5. *isDualAuth* .

OnCheckGlobalAPBViolationByDoorOpen

가 , 1

```
typedef void (*OnCheckGlobalAPBViolationByDoorOpen)(uint32_t deviceId,  
uint16_t seq, const char* userID_1, const char* userID_2, bool isDualAuth);
```

1. *deviceId*

2. *seq*

3. *userID_1*

ID .

4. *userID_2*

ID .

5. *isDualAuth*

OnUpdateGlobalAPBViolationByDoorOpen

가 , 2

```
typedef void (*OnUpdateGlobalAPBViolationByDoorOpen)(uint32_t deviceId,  
uint16_t seq, const char* userID_1, const char* userID_2, bool isDualAuth);
```

1. *deviceId*

2. *seq*

3. *userID_1*

ID .

4. *userID_2*

ID .

5. *isDualAuth*

BS2ZoneStatus

```
typedef struct {
    uint32_t id;
    uint8_t status;
    uint8_t disabled;
    uint8_t reserved[6];
} BS2ZoneStatus;
```

1. *id*

2. *status*

0	
1	
2	scheduled lock
4	scheduled unlock

3. *disabled*

flag

4. *reserved*

BS2ApbMember

```
typedef struct {
    uint32_t deviceID;
    uint8_t type;
    uint8_t reserved[3];
} BS2ApbMember;
```

1. *deviceID*

2. *type*

APB reader

-1	
0	
1	

3. *reserved*

BS2TimedApbMember

```
typedef struct {
    uint32_t deviceID;
    uint8_t reserved[4];
} BS2TimedApbMember;
```

1. *deviceID*

2. *reserved*

BS2FireSensor

```
typedef struct {
    uint32_t deviceID;
    uint8_t port;
    uint8_t switchType;
    uint8_t duration;
} BS2FireSensor ;
```

1. *deviceID*

2. *port*

3. *switchType*

0	
1	

4. *duration*

millisecond

BS2AntiPassbackZone

```
typedef struct {
    uint32_t zoneID;
    char name[BS2_MAX_ZONE_NAME_LEN];
    uint8_t type;
    uint8_t numReaders;
```

```
uint8_t numBypassGroups;
uint8_t disabled;
uint8_t alarmed;
uint8_t reserved[3];
uint32_t resetDuration;
BS2Action alarm[BS2_MAX_APB_ALARM_ACTION];
BS2ApbMember readers[BS2_MAX_READERS_PER_APB_ZONE];
uint8_t reserved2[512];
uint32_t bypassGroupIDs[BS2_MAX_BYPASS_GROUPS_PER_APB_ZONE];
} BS2AntiPassbackZone;
```

1. zoneID

1 가 .

가 .

2. name

BioStar .

3. type

0	Hard APB(가)
1	Soft APB()

4. numReaders

APB reader .

5. numBypassGroups

APB .

6. disabled

flag .

7. alarmed

.

8. reserved

.

9. resetDuration

APB () , 0 , BS2_ClearAntiPassbackZoneStatus .

10. <i>alarm</i>	가 APB	5	.
11. <i>readers</i>		64	.
12. <i>reserved2</i>			.
13. <i>bypassGroupIDs</i>	APB	16	.

BS2TimedAntiPassbackZone

```
typedef struct {
    uint32_t zoneID;
    char name[BS2_MAX_ZONE_NAME_LEN];
    uint8_t type;
    uint8_t numReaders;
    uint8_t numBypassGroups;
    uint8_t disabled;
    uint8_t alarmed;
    uint8_t reserved[3];
    uint32_t resetDuration;
    BS2Action alarm[BS2_MAX_TIMED_APB_ALARM_ACTION];
    BS2TimedApbMember readers[BS2_MAX_READERS_PER_TIMED_APB_ZONE];
    uint8_t reserved2[320];
    uint32_t bypassGroupIDs[BS2_MAX_BYPASS_GROUPS_PER_TIMED_APB_ZONE];
} BS2TimedAntiPassbackZone;
```

1. *zoneID*

1	가	.
---	---	---

2. *name*

BioStar

.

3. *type*

.

0	Hard APB(가)
1	Soft APB()

4. *numReaders*

reader	.
--------	---

5. *numBypassGroups*

.

6. *disabled*

flag

7. *alarmed*8. *reserved*9. *resetDuration*

가

0

BioStar

10. *alarm*

가

5

11. *readers*

64

12. *reserved2*13. *bypassGroupIDs*

16

BS2FireAlarmZone

```
typedef struct {
    uint32_t zoneID;
    char name[BS2_MAX_ZONE_NAME_LEN];
    uint8_t numSensors;
    uint8_t numDoors;
    uint8_t disabled;
    uint8_t alarmed;
    uint8_t reserved[8];
    BS2FireSensor sensor[BS2_MAX_FIRE_SENSORS_PER_FIRE_ALARM_ZONE];
    BS2Action alarm[BS2_MAX_FIRE_ALARM_ACTION];
    uint8_t reserved2[32];
    uint32_t doorIDs[BS2_MAX_DOORS_PER_FIRE_ALARM_ZONE];
} BS2FireAlarmZone;
```

1. *zoneID*

1

가

2. *name*

BioStar

3. *numSensors*

4. numDoors

5. alarmed

6. disabled
flag

7. reserved

8. sensor
8

9. alarm
5

10. reserved2

11. doorIDs
32

BS2ScheduledLockUnlockZone

```
typedef struct {
    uint32_t zoneID;
    char name[BS2_MAX_ZONE_NAME_LEN];
    uint32_t lockScheduleID;
    uint32_t unlockScheduleID;
    uint8_t numDoors;
    uint8_t numBypassGroups;
    uint8_t numUnlockGroups;
    uint8_t bidirectionalLock;
    uint8_t disabled;
    uint8_t alarmed;
    uint8_t reserved[6];
    BS2Action alarm[BS2_MAX_SCHEDULED_LOCK_UNLOCK_ALARM_ACTION];
    uint8_t reserved2[32];
    uint32_t doorIDs[BS2_MAX_DOORS_IN_SCHEDULED_LOCK_UNLOCK_ZONE];
    uint32_t
bypassGroupIDs[BS2_MAX_BYPASS_GROUPS_IN_SCHEDULED_LOCK_UNLOCK_ZONE];
    uint32_t
unlockGroupIDs[BS2_MAX_UNLOCK_GROUPS_IN_SCHEDULED_LOCK_UNLOCK_ZONE];
} BS2ScheduledLockUnlockZone;
```

1. zoneID
1가

2. name
BioStar

3. <i>lockScheduleID</i>			
4. <i>unlockScheduleID</i>			
5. <i>numDoors</i>			
6. <i>numBypassGroups</i>			
7. <i>numUnlockGroups</i>			
8. <i>bidirectionalLock</i>			
9. <i>disabled</i>			
flag			
10. <i>alarmed</i>			
11. <i>reserved</i>			
12. <i>alarm</i>			
	5		
13. <i>reserved2</i>			
14. <i>doorIDs</i>			
	32		
15. <i>bypassGroupIDs</i>			
		16	
16. <i>unlockGroupIDs</i>			
16			

BS2IntrusionAlarmZone

```
typedef struct {
    uint32_t zoneID;
    char name[BS2_MAX_ZONE_NAME_LEN];
    uint8_t armDelay;
    uint8_t alarmDelay;
    uint8_t disabled;
    uint8_t reserved[1];
}
```

```

uint8_t numReaders;
uint8_t numInputs;
uint8_t numOutputs;
uint8_t numCards;
uint8_t numDoors;
uint8_t numGroups;
uint8_t reserved2[10];
} BS2IntrusionAlarmZone;

```

1. *zoneID*

1 가 .

2. *name*

BioStar .

3. *armDelay*

.

4. *alarmDelay*

.

5. *disabled*

flag .

6. *reserved[1]*

.

7. *numReaders*

.

8. *numInputs*

.

9. *numOutputs*

.

10. *numCards*

.

11. *numDoors*

.

12. *numGroups*

.

13. *reserved*

.

BS2IntrusionAlarmZoneBlob

```

typedef struct {
    BS2IntrusionAlarmZone IntrusionAlarmZone;
}

```

```
BS2AlarmZoneMember* memberObjs;
BS2AlarmZoneInput* inputObjs;
BS2AlarmZoneOutput* outputObjs;
BS2CSNCard* cardObjs;
BS2_D00R_ID* doorIDs;
BS2_ACCESS_GROUP_ID* groupIDs;
} BS2IntrusionAlarmZoneBlob;
```

1. *IntrusionAlarmZone*

2. *memberObjs*

IntrusionAlarmZone.numReaders

3. *inputObjs*

IntrusionAlarmZone.numInputs

4. *outputObjs*

IntrusionAlarmZone.numOutputs

5. *cardObjs*

IntrusionAlarmZone.numCards

[Smartcard API](#)

6. *doorIDs*

IntrusionAlarmZone.numDoors

7. *groupIDs*

IntrusionAlarmZone.numGroups

BS2InterlockZone

```
typedef struct {
    uint32_t zoneID;
    char name[BS2_MAX_ZONE_NAME_LEN];
    uint8_t disabled;
    uint8_t numInputs;
    uint8_t numOutputs;
    uint8_t numDoors;
    uint8_t reserved[8];
} BS2InterlockZone;
```

1. *zoneID*

1 가 .

2. *name*

BioStar

3. *disabled*

flag

4. *numInputs*

5. *numOutputs*

6. *numDoors*

7. *reserved*

BS2InterlockZoneBlob

```
typedef struct {  
    BS2InterlockZone InterlockZone;  
    BS2InterlockZoneInput* inputObjs;  
    BS2InterlockZoneOutput* outputObjs;  
    BS2_D00R_ID* doorIDs;  
} BS2InterlockZoneBlob;
```

1. *InterlockZone*

2. *inputObjs*

InterlockZone.numInputs

3. *outputObjs*

InterlockZone.numOutputs

4. *doorIDs*

InterlockZone.numDoors

BS2DeviceZoneEntranceLimitMaster

```
typedef struct {  
    char name[BS2_MAX_ZONE_NAME_LEN];  
    uint8_t type;  
    uint8_t reserved1[3];  
    uint32_t entryLimitInterval_s;  
    uint8_t numEntranceLimit;
```

```
uint8_t numReaders;
uint8_t numAlarm;
uint8_t numBypassGroups;
uint8_t maxEntry[BS2_MAX_ENTRANCE_LIMIT_PER_ZONE];
uint32_t periodStart_s[BS2_MAX_ENTRANCE_LIMIT_PER_ZONE];
uint32_t periodEnd_s[BS2_MAX_ENTRANCE_LIMIT_PER_ZONE];
BS2DeviceZoneEntranceLimitMemberInfo
readers[BS2_MAX_READERS_PER_DEVICE_ZONE_ENTRANCE_LIMIT];
BS2Action alarm[BS2_MAX_DEVICE_ZONE_ENTRANCE_LIMIT_ALARM_ACTION];
BS2_ACCESS_GROUP_ID
bypassGroupIDs[BS2_MAX_BYPASS_GROUPS_PER_DEVICE_ZONE_ENTRANCE_LIMIT];
uint8_t reserved3[8 * 4];
} BS2DeviceZoneEntranceLimitMaster;
```

1. *name*
BioStar

2. *type*

1	Soft EntranceLimit(가)
2	Hard EntranceLimit()

3. *reserved1[3]*

4. *entryLimitInterval_s*

5. *numEntranceLimit*

6. *numReaders*
reader

7. *numAlarm*

8. *numBypassGroups*

9. *maxEntry*

10. *periodStart_s*
가 ()

11. *periodEnd_s*
가 ()


```

    BS2DeviceZoneFireAlarmMemberInfo
    readers[BS2_MAX_READERS_PER_DEVICE_ZONE_FIRE_ALARM];
    BS2Action alarm[BS2_MAX_DEVICE_ZONE_FIRE_ALARM_ALARM_ACTION];
    uint8_t reserved2[8 * 40];
} BS2DeviceZoneFireAlarmMaster;

```

1. *name*

BioStar

2. *numReaders*

3. *reserved1*

4. *readers*

5. *alarm*

5

6. *reserved2*

BS2DeviceZoneFireAlarmMember

```

typedef struct {
    BS2_PORT masterPort;
    uint8_t reserved1[2];
    BS2_IPV4_ADDR masterIP;
    uint8_t numSensors;
    uint8_t numDoors;
    uint8_t reserved2[2];
    BS2DeviceZoneFireSensor
sensor[BS2_MAX_FIRE_SENSORS_PER_DEVICE_ZONE_FIRE_ALARM_MEMBER];
    union {
        BS2_D00R_ID
doorIDs[BS2_MAX_DOORS_PER_DEVICE_ZONE_FIRE_ALARM_MEMBER];
        BS2_LIFT_ID
liftIDs[BS2_MAX_DOORS_PER_DEVICE_ZONE_FIRE_ALARM_MEMBER];
    };
} BS2DeviceZoneFireAlarmMember;

```

1. *masterPort*

master port

2. *reserved1*

3. *masterIP*

master IP .

4. numSensors

5. numDoors

6. reserved2

7. sensor 8

8. doorIDs 8

9. liftIDs 8
Lift

BS2DeviceZoneFireAlarmMemberInfo

```
typedef struct {
    uint32_t readerID;
} BS2DeviceZoneFireAlarmMemberInfo;
```

1. readerID

BS2DeviceZoneFireSensor

```
typedef struct {
    uint32_t deviceID;
    uint8_t port;
    uint8_t switchType;
    uint16_t duration;
} BS2DeviceZoneFireSensor;
```

1. deviceID

2. port

3. switchType

0	

1	

4. duration

millisecond

.

BS2DeviceZone

```
typedef struct {
    uint32_t zoneID;
    uint8_t zoneType;
    uint8_t nodeType;
    uint8_t enable;
    uint8_t reserved[1];
    union {
        BS2DeviceZoneEntranceLimitMaster entranceLimitMaster;
        BS2DeviceZoneEntranceLimitMember entranceLimitMember;
        BS2DeviceZoneFireAlarmMaster fireAlarmMaster;
        BS2DeviceZoneFireAlarmMember fireAlarmMember;
    };
} BS2DeviceZone;
```

1. zoneID

1

가

.

2. zoneType

.

3. nodeType

.

4. enable

flag

.

5. reserved[1]

.

BS2DeviceZoneAGEntranceLimit

```
typedef struct {
    uint32_t zoneID;
    uint16_t numAGEntranceLimit;
    uint16_t reserved1;
    uint32_t periodStart_s[BS2_MAX_ENTRANCE_LIMIT_PER_ZONE];
    uint32_t periodEnd_s[BS2_MAX_ENTRANCE_LIMIT_PER_ZONE];
    uint16_t numEntry[BS2_MAX_ENTRANCE_LIMIT_PER_ZONE];
    uint16_t
maxEntry[BS2_MAX_ENTRANCE_LIMIT_PER_ZONE][BS2_MAX_ACCESS_GROUP_ENTRANCE_LIMI
```

```
T_PER_ENTRANCE_LIMIT];
uint32_t
accessGroupID[BS2_MAX_ENTRANCE_LIMIT_PER_ZONE][BS2_MAX_ACCESS_GROUP_ENTRANCE
_LIMIT_PER_ENTRANCE_LIMIT];
} BS2DeviceZoneAGEntranceLimit;
```

1. zoneID
- 1가.
2. numAGEntranceLimit
- .
3. reserved1
- .
4. periodStart_s
- 가.
5. periodEnd_s
- 가.
6. numEntry
- .
7. maxEntry
- .
8. accessGroupID
- 16

BS2LiftFloors

```
typedef struct {
    uint32_t liftID;
    uint16_t numFloors;
    uint16_t reserved;
    uint8_t floorIndices[256];
} BS2LiftFloors;
```

1. liftID
- lift1가.
2. numFloors
- floorIndices.
3. reserved
- .
4. floorIndices
- BS2LiftBS2LiftFloor 255floor
- , 1, 3, 5, 9BS2LiftFloorscheduled lock/unlockfloor.

floorIndices[0]1, 3, 5, 9.

BS2LiftLockUnlockZone

```
typedef struct {
    uint32_t zoneID;
    char name[BS2_MAX_ZONE_NAME_LEN];
    uint32_t unlockScheduleID;
    uint32_t lockScheduleID;

    uint8_t numLifts;
    uint8_t numBypassGroups;
    uint8_t numUnlockGroups;
    uint8_t unused;

    uint8_t disabled;
    uint8_t alarmed;
    uint8_t reserved[6];

    BS2Action alarm[BS2_MAX_LIFT_LOCK_UNLOCK_ALARM_ACTION];

    uint8_t reserved2[32];

    BS2LiftFloors lifts[BS2_MAX_LIFTS_IN_LIFT_LOCK_UNLOCK_ZONE];
    uint32_t bypassGroupIDs[BS2_MAX_BYPASS_GROUPS_IN_LIFT_LOCK_UNLOCK_ZONE];
    uint32_t unlockGroupIDs[BS2_MAX_UNLOCK_GROUPS_IN_LIFT_LOCK_UNLOCK_ZONE];
} BS2LiftLockUnlockZone;
```

1. zoneID1가.
2. nameBioStar.
3. unlockScheduleIDlift floor.
4. lockScheduleIDlift floor.
5. numLiftslifts.
6. numBypassGroupslift.
7. numUnlockGroupslift가.

8. unused	.		
9. disabled	flag	.	
10. alarmed	.		
11. reserved	.		
12. alarm		5	.
13. reserved2	.		
14. lifts			
lift	floor	.	
15. bypassGroupIDs			
lift			16
16. unlockGroupIDs			
lift		가	
16	.		

From:

<https://kb.supremainc.com/kbtest/> - **BioStar Device SDK**

Permanent link:

https://kb.supremainc.com/kbtest/doku.php?id=ko:zone_control_api&rev=1609810216

Last update:

2021/01/05 10:30