## **Table of Contents**

/

Supports Dynamic Site Configuration	1
Dynamic Site Policy	1
How To Issue Dynamic Card	3

## **Supports Dynamic Site Configuration**

Suprema officially supports Suprema Mobile Access Dynamic Site from BioStar 2.8.9.

		Site Type	DYNAMIC
Site Type	DYNAMIC	Dent.	Difference
Port	443	• Port	443
		• Email	yu1yu@supr
			Cop
	- Site Type - Port	• Site Type DYNAMIC • Port 443	Site Type     DYNAMIC     Port     443     Email

## **Dynamic Site Policy**

- **Dynamic Site** allows you to reissue, revoke, or discontinue mobile access cards or specify the expiration date of it. It deducts credits according to the period of use or devices. Dynamic can be used in gyms, libraries, or shared facilities where it provides membership services.
- The BioStar 2 server needs to be connected to the Internet and run **ONLY** when issuing or deleting a Dynamic Card.
- Mobile devices for which Dynamic Cards have been issued must ALWAYS be connected to the Internet. In unavoidable cases, a maximum exception time of 5 minutes is allowed, but after that, it will be marked as network disconnected and the access card cannot be used.
- There is only one site that can be registered in BioStar 2> Settings> Mobile Access. Dynamic Site and Regular Site cannot be connected together in one BioStar 2 server.
- If you create a Dynamic Site on Airfob Portal, you can issue a Suprema Mobile Access card for free for **1 MONTH** without purchasing a license. When the free trial period has expired, and if you have not purchased a separate credit for the Dynamic Site, you will be notified as follows:
  - BioStar 2 : Alert message will show if administrator tries to issue or delete mobile access card. (The site is currently under payment required status. Please change the site's credit from the Airfob Portal and try again.)
  - Airfob Portal : Free usage period expiration email sent to Dynamic Site administrator account.
  - Airfob Pass : Card issued at Dynamic Site is changed now to suspended.

• The credit deduction method of Dynamic site is different from Regular.

<b>Card Issuance Limitation</b>	Unlimited
<b>Credit Deduction Policy</b>	1 Credit deduction per device registered
Billing Method	Monthly *Contact Sales Representative for further details.(Link)

- Detailed description about difference between Dynamic Site and Regular Site:Related Article
  - If the dynamic site is connected, when the Mobile Access Card is issued, the message about credit deduction is **NOT** confirmed. (Same for both issuing directly from the user page and issuing through CSV.)
  - If the dynamic site is connected, you must enter the expiration date of the Mobile Access Card.
  - When batch issuing a Mobile Access Card for a Dynamic Site through CSV Import, the import **FAILS** if there is no information about **the start and end date of the validity period for the card**.

user_id name department user_title phone email user_groustart_datetime expiry_datetime mobile_start_datetime mobile_expiry_datetime	
	csn_mobile
1 Administrator All Users 1/1/2001 0:00 12/31/2030 23:59	
2 Suprema Mobile Access Test Suprema Test Engineer jhlee2@sup All Users 1/1/2001 0:00 12/31/2030 23:59 12/31/2020 14:14 3/18/2023 14:14	2

After creating a dynamic site, even if a device is added, the credit is verified as 0. Even if the credit is 0, you CAN proceed with issuing and authenticating a Mobile Access Card for the Dynamic Site for free for 1 MONTH.

Portal		
	License	
Current Site Dynamic	Credit Status	Device Status
(O) Users ~	Credit	Registered Device
Registered Device ~	U	- <b>-</b>

## How To Issue Dynamic Card

**Step 1**> Go to the Airfob Portal and create a Dynamic Site. (Airfob Portal : https://mc.mocainc.com/signin)

How to create Airfob Portal Site (Related Article)

ama	
	Site Settings
	Please configure the site settings considering the site characteristics. Site can be configured to use only one type of card.
	Dynamic
	Back Create →

**Step 2**> Go to BioStar 2 > Settings > Mobile Access and connect with your Dynamic Site you created at **Step 1**.

Mobile Acces	5					
General						
Mobile Acces	s Setting 🚺 Use		Site Type	DYNAMIC		
- Domain	https://api.mc.suprema.io		• Port	443		
Site ID	2834		• Email	testtest@testemail.com		
Password				Connect		
Device Regist	ration Device ID	Device Name		Device Group	IP Address	+ Add
			Not found			

**Step 3**> Go to BioStar 2 > Settings > Mobile Access and add your device which supports Suprema Mobile Access.

2024/01/03 19:40

4/7

Mobile Access							
General							
Mobile Access Setting  Us	Se	- Site Type					
Domain     https://	//api.mc.suprema.io	- Port	443				
• Site ID 2834		- Email	testtest@testemail.com				
Password			Connect				
Device Registration	Device ID Devic	e Name		Device Group	IP Address		+ Add
	802 BioLite N2 802	BioLite N2 802 (192.168.8.195)			192.168.8.195	0.	

- Confirm your device is right model and right firmware version.
- Related Article: Supported Devices List of Mobile Access
- Device list in the Airfob Portal will be automatically updated.

Portal			HI, Laney
	15 ~ < 1 / 1	•	
Dy	Product Name     ^	Model Name	Device ID
Current Site Dynamic	802	BLN2-OAB	802
(8) Users 🗸			
Registered Device ^			
Registered Devices			

**Step 4>** Add a user from the BioStar 2> User menu.

- Essentials: Name and email address
- Optional: User profile image, department, job title information

BioStar 2	) Settings 🖉 Port	) About (?) Help					
DASH BOARD	← Suprema Mot	bile Access Te	est	Red Items : Mandatory for	Supre	ema Mobile	Access
A una	Information			Blue Items : Option for Mo	bile A	ccess card	registration
R		- Name	Suprema Mobile Access Test			• Email	cardtest@testemail.com
DEVICE		Department	Suprema Test			• Title	Test Engineer
DOOR		• ID	2			Telephone	
m		- Group	All Users	,	r	Status	Active
ELEVATOR	/	- Period	2001/01/01 00:00	~ 2030/12/31 23:59			
0		Operator Level	None		r	Access Group	
		User IP					

**Step 5>** Enroll Mobile Access Card.

- Can choose between manually entering card ID or using random card ID.
- Can choose whether you will refer to profile photo, department and job title. (You can **ONLY** choose when you enroll user with each item.)
- Need to configure validity period for Mobile Access Card in Dynamic Site.

Enroll Card		×
Card Type	CSN Mobile 👻	
Registration     Option	Enter Manually	
Card ID		- I
Card ID	2 Use User ID	
Input Type	Enter manually	
Information		
Photo	Use Use	
Department	Suprema Test Toggle : Use OR Not Use	
• Title	Test Engineer	
For Dynamic Cards		<b>-</b>
Period		
Expiry Period	+1 Day +7 Days +30 Days +1 Year	
Period	2020/12/31 14:14 ~ 2023/03/18 14:14	
		_
	Enroll Cancel	

**Step 6**> After completing the card issuance in BioStar 2, access the Airfob Portal to check if the card issuance was successful.

- **Before Activation** : Mobile Access Card download link is sent to the user and the download has not yet been received.
- Activated : The user has downloaded the Mobile Access Card to the mobile phone.

					III, Laney 🚺	Ð
Search		15 ~ ( 1 / 1 >		Total Users: 1	Add User	1
User Info			Card ID	Valid Thru	Card Status	
	ID Name Title	198288 Suprema Mobile Access Test Test Engineer Suprema Test	2	Start 2020/12/31 - 14:14 Expire 2023/03/18 - 14:14	Before Activation	
	Search User Info	Search User Info ID Name Title Department	Search 15 v ( 1 / 1 ) User Info ID 198288 Name Suprema Mobile Access Test Title Test Engineer Department Suprema Test	Search 15 ° (1/1) User Info Card ID ID 198288 Name Suprema Mobile Access Test Title Test Engineer Department Suprema Test	Search     15 v (1/1)     Total Users:1       User Info     v     Card ID     Valid Thru       ID     198288     Name     Suprema Mobile Access Test     2       Title     Test Engineer     2020/12/31-14:14       Department     Suprema Test     2	Search     15 v (1/1)     Total Users: 1     Add User       User Info     v     Card ID     Valid Thru     Card Status       ID     198288     Name     Suprema Mobile Access Test     2     Start     2020/12/31-14:14     Before Activation       Title     Test Engineer     Suprema Test     2     Start     2023/03/18-14:14     Before Activation

**Step 7**> Open the mailbox on your phone and download the Mobile Access Card. There are two ways to download:

- 1. Click the download button in the email. (Related Article)
- 2. Use an activation code. (Related Article)



• Need to configure validity period for Mobile Access Card in Dynamic Site.

Portal								
Current Site Dynamic & Users	×	٩	Search		15 ~ ( 1 / 1	•	Total Users: 1	
			User Info		~	Card ID	Valid Thru	Card Status
				ID Name	198288 Suprema Mobile Access Test	2	Start 2020/12/31 - 14:14	Activated
				Title Department	Test Engineer Suprema Test		Expire 2023/03/18 - 14:14	

7/7

Supports Dynamic Site Configuration

**Step 8**> Turn on the phone's NFC or BLE function and authenticate the Mobile Access Card to the device registered in **Step 3**. You can check the user authentication log in BioStar 2> Monitoring.

o Real-time Log								
Y Save Filter							II Pause 👱	·/ <b>b</b>
Date						Event		View TNA Key
2020/12/31 14:23:25		802	BioLite N2 802	2(Suprema Mobile Access Test)		1:1 authentication succeeded (Card)		
2020/12/31 14:23:20		802	BioLite N2 802	2(Suprema Mobile Access Test)		1:1 authentication succeeded (Card)		
2020/12/31 14:23:15		802	BioLite N2 802	2(Suprema Mobile Access Test)		1:1 authentication succeeded (Card)		
2020/12/31 14:22:56		802	BioLite N2 802	2(Suprema Mobile Access Test)		1:1 authentication succeeded (Card)		
2020/12/31 14:22:47		802	BioLite N2 802	2(Suprema Mobile Access Test)		1:1 authentication succeeded (Card)		

From: https://kb.supremainc.com/knowledge/ -

Permanent link: https://kb.supremainc.com/knowledge/doku.php?id=en:supports\_dynamic\_site\_configuration&rev=1610590150

Last update: 2021/01/14 11:09

2024/01/03 19:40