# **Table of Contents**

How to upgrade device firmware in BioStar 2	 1
15	

### BioStar 2, firmware, upgrade

## How to upgrade device firmware in BioStar 2

Firmware files are provided with an installation of the official version of BioStar 2, but if you have custom or more recent firmware files that you would like to use, you can follow the procedure below to apply it to your device.

- 1. In File explorer go to the path below.
- C:\Program Files (x86)\BioStar 2\firmware
- 2. Copy and paste the provided firmware file into this folder.
- 3. Log in to BioStar 2.
- 4. In **DEVICE** menu check the device you want to upgrade and click **Firmware Upgrade**.

BioStar	2 💮 Setting (7 About (	⊙ Help								Administrator (Right Third)
DASH BOARD		All D	evices			0.0	- Company	the second second second	1-4/4	Go Go
R	All Devices		Device ID	Name		Group	C sync Device	Device Type (Master/Slave)	IP Address	Device Status
Ģ	BioEntryW 10006 (192.168		10006	BioEntryW 10006 (192.168.16.188)	All Devices		BioE	ntryW 19	2.168.16.188	Disconnected
DEVICE	BioLiteNet 538101263 (192.		539552319	BioEntryPlus 539552319 (192.168.16.223)	All Devices		BioE	ntryPlus 19	2.168.16.223	Disconnected
DOOR	Waiting Device		546834329	BioStation 2 546834329 (192.168.16.191)	All Devices		BioS	tation 2 🔟 19	2.168.16.191	Disconnected

5. Click on the desired firmware version to start the upgrade.

mware Upgrade		
EntryPlus 539552319 (192.168	.16.223)	
Device Type	Firmware Version	
BioEntryPlus (BEPM-OC)	2.2.3	
Close		

6. Wait for the device to upgrade and restart.

If a hotfix version of firmware is based on same version of the recent firmware, you will not be able to distinguish it on the Firmware Upgrade popup. In this case, delete or move the older firmware file to another folder avoid confusion.



From: http://kb.supremainc.com/knowledge/ -

Permanent link: http://kb.supremainc.com/knowledge/doku.php?id=en:2xfaq\_how\_to\_upgrade\_device\_firmware\_in\_biostar\_2&rev=1469410230

Last update: 2016/07/25 10:30