

目次

デバイスのファームウェアを一度にアップグレード	1
-------------------------------	---

デバイスのファームウェアを一度にアップグレード

システムとデバイスの安全性および性能を考慮して、ファームウェアは常に最新バージョンで使用しなければなりません。しかし、数百台のデバイスが設置されている場合、デバイスのファームウェアのアップグレードは容易ではありません。

BioStar2は簡単な方法で複数のデバイスのファームウェアを一度にアップグレードすることができます。

- 同じ種類のデバイスのみを選択しなければなりません。デバイスモデルの種類とサポートするカードの種類が必ず同一でなければなりません。
例) BioStation A2-OMPW

1. デバイスリストからアップグレードするデバイスを選択してください。

The screenshot shows the 'All Devices' management interface. At the top, there are navigation controls (1 / 1), a '50 rows' dropdown, and a 'Go' button. Below these are action buttons: 'Sync Device', 'Batch Edit', 'Firmware Upgrade', 'Delete Device', and a menu icon. The main part of the interface is a table with the following columns: Device ID, Name, Group, Device Type (Master/Slave), IP Address, and Device Status. Five devices are listed, with checkboxes in the first column. The second, third, and fifth rows have their checkboxes checked and are highlighted with a red border.

<input type="checkbox"/>	Device ID	Name	Group	Device Type (Master/Slave)	IP Address	Device Status
<input type="checkbox"/>	540084003	BioStation L2 540084003 ...	All Devices	BioStation L2	192.168.14...	Disconnected
<input checked="" type="checkbox"/>	541531096	BioStation A2 541531096 ...	All Devices	BioStation A2	192.168.14...	Normal
<input checked="" type="checkbox"/>	541531114	BioStation A2 541531114 ...	All Devices	BioStation A2	192.168.14...	Disconnected
<input type="checkbox"/>	544108117	BioEntry W2 544108117 (...)	All Devices	BioEntry W2	192.168.14...	Normal
<input checked="" type="checkbox"/>	939254152	BioStation A2 939254152 ...	All Devices	BioStation A2 M	192.168.14...	Disconnected

2. ファームウェアのアップグレード(Firmware Upgrade)ボタンをクリックしてください。

All Devices

Navigation: 1 / 1, 50 rows, Go

Actions: Sync Device, Batch Edit, **Firmware Upgrade**, Delete Device, ...

	Device ID	Name	Group	Device Type (Master/Slave)	IP Address	Device Status
<input type="checkbox"/>	540084003	BioStation L2 540084003 ...	All Devices	BioStation L2	192.168.14...	Disconnected
<input checked="" type="checkbox"/>	541531096	BioStation A2 541531096 ...	All Devices	BioStation A2	192.168.14...	Normal
<input checked="" type="checkbox"/>	541531114	BioStation A2 541531114 ...	All Devices	BioStation A2	192.168.14...	Disconnected
<input type="checkbox"/>	544108117	BioEntry W2 544108117 (...)	All Devices	BioEntry W2	192.168.14...	Normal
<input checked="" type="checkbox"/>	939254152	BioStation A2 939254152 ...	All Devices	BioStation A2 M	192.168.14...	Disconnected

3. デバイスに適用するファームウェアのバージョンを選択してください。

Firmware Upgrade [X]


Devices (3)

Device Type	Firmware Version
BioStation A2 (BSA2-OMPW)	1.2.1 [2016/09/21 13:13]
BioStation A2 (BSA2-OMPW)	1.2.0 [2016/07/07 17:21]

Close

4. はい(Yes)をクリックして、ファームウェアのアップグレードを行ってください。

Confirm [X]

 Are you sure you want to firmware upgrade?

Yes No

5. ファームウェアのアップグレードが完了すると、以下のようなメッセージが表示されます。

Information



Firmware upgrade was successful.

Ok

From:

<https://kb.supremainc.com/knowledge/> -

Permanent link:

https://kb.supremainc.com/knowledge/doku.php?id=ja:how_to_batch_upgrade_devices

Last update: **2019/09/30 09:23**